
AdafruitDS18X20 Library Documentation

Release 1.0

Carter Nelson

Feb 25, 2021

Contents

| | | |
|----------|----------------------------|-----------|
| 1 | Dependencies | 3 |
| 2 | Usage Example | 5 |
| 3 | Contributing | 7 |
| 4 | Documentation | 9 |
| 5 | Table of Contents | 11 |
| 5.1 | Simple test | 11 |
| 5.2 | adafruit_ds18x20 | 12 |
| 6 | Indices and tables | 15 |
| | Python Module Index | 17 |
| | Index | 19 |

CircuitPython driver for Dallas 1-Wire temperature sensor.

CHAPTER 1

Dependencies

This driver depends on:

- Adafruit CircuitPython
- Adafruit OneWire

Please ensure all dependencies are available on the CircuitPython filesystem. This is easily achieved by downloading the Adafruit library and driver bundle.

CHAPTER 2

Usage Example

```
import board
from adafruit_onewire.bus import OneWireBus
from adafruit_ds18x20 import DS18X20
ow_bus = OneWireBus(board.D2)
ds18 = DS18X20(ow_bus, ow_bus.scan()[0])
ds18.temperature
```


CHAPTER 3

Contributing

Contributions are welcome! Please read our [Code of Conduct](#) before contributing to help this project stay welcoming.

CHAPTER 4

Documentation

For information on building library documentation, please check out [this guide](#).

CHAPTER 5

Table of Contents

5.1 Simple test

Ensure your device works with these simple tests.

Listing 1: examples/ds18x20_simpletest.py

```
1 # SPDX-FileCopyrightText: 2020 ladyada for Adafruit Industries
2 # SPDX-License-Identifier: MIT
3
4 # Simple demo of printing the temperature from the first found DS18x20 sensor every
5 # second.
6 # Author: Tony DiCola
7
8 # A 4.7Kohm pullup between DATA and POWER is REQUIRED!
9
10 import time
11 import board
12 from adafruit_onewire.bus import OneWireBus
13 from adafruit_ds18x20 import DS18X20
14
15 # Initialize one-wire bus on board pin D5.
16 ow_bus = OneWireBus(board.D5)
17
18 # Scan for sensors and grab the first one found.
19 ds18 = DS18X20(ow_bus, ow_bus.scan()[0])
20
21 # Main loop to print the temperature every second.
22 while True:
23     print("Temperature: {:.0f}C".format(ds18.temperature))
24     time.sleep(1.0)
```

Listing 2: examples/ds18x20_asynctest.py

```
1 # SPDX-FileCopyrightText: 2020 ladyada for Adafruit Industries
2 # SPDX-License-Identifier: MIT
3
4 # Simple demo of printing the temperature from the first found DS18x20 sensor every ↴
5 # second.
6 # Using the asynchronous functions start_temperature_read() and
7 # read_temperature() to allow the main loop to keep processing while
8 # the conversion is in progress.
9 # Author: Louis Bertrand, based on original by Tony DiCola
10
11 # A 4.7Kohm pullup between DATA and POWER is REQUIRED!
12
13 import time
14 import board
15 from adafruit_onewire.bus import OneWireBus
16 from adafruit_ds18x20 import DS18X20
17
18 # Initialize one-wire bus on board pin D1.
19 ow_bus = OneWireBus(board.D1)
20
21 # Scan for sensors and grab the first one found.
22 ds18 = DS18X20(ow_bus, ow_bus.scan()[0])
23 ds18.resolution = 12
24
25 # Main loop to print the temperature every second.
26 while True:
27     conversion_delay = ds18.start_temperature_read()
28     conversion_ready_at = time.monotonic() + conversion_delay
29     print("waiting", end="")
30     while time.monotonic() < conversion_ready_at:
31         print(".", end="")
32         time.sleep(0.1)
33     print("\nTemperature: {0:0.3f}C\n".format(ds18.read_temperature()))
34     time.sleep(1.0)
```

5.2 adafruit_ds18x20

Driver for Dallas 1-Wire temperature sensor.

- Author(s): Carter Nelson

class adafruit_ds18x20.DS18X20(*bus, address*)
Class which provides interface to DS18X20 temperature sensor.

read_temperature()

Read the temperature. No polling of the conversion busy bit (assumes that the conversion has completed).

resolution

The programmable resolution. 9, 10, 11, or 12 bits.

start_temperature_read()

Start asynchronous conversion, returns immediately. Returns maximum conversion delay [seconds] based on resolution.

temperature

The temperature in degrees Celsius.

CHAPTER 6

Indices and tables

- genindex
- modindex
- search

Python Module Index

a

adafruit_ds18x20, 12

Index

A

`adafruit_ds18x20` (*module*), 12

D

`DS18X20` (*class in adafruit_ds18x20*), 12

R

`read_temperature()` (*adafruit_ds18x20.DS18X20 method*), 12

`resolution` (*adafruit_ds18x20.DS18X20 attribute*),
12

S

`start_temperature_read()`
(*adafruit_ds18x20.DS18X20 method*), 12

T

`temperature` (*adafruit_ds18x20.DS18X20 attribute*),
12