

---

# **Adafruit MCP9808 Library Documentation**

***Release 1.0***

**Phillip Moyer**

**Apr 10, 2020**



---

## Contents

---

<b>1</b>	<b>Dependencies</b>	<b>3</b>
<b>2</b>	<b>Installing from PyPI</b>	<b>5</b>
<b>3</b>	<b>Usage Notes</b>	<b>7</b>
<b>4</b>	<b>Contributing</b>	<b>9</b>
<b>5</b>	<b>Documentation</b>	<b>11</b>
<b>6</b>	<b>Table of Contents</b>	<b>13</b>
6.1	Simple test . . . . .	13
6.2	adafruit_mcp9808 - MCP9808 I2C Temperature Sensor . . . . .	13
6.2.1	Implementation Notes . . . . .	14
<b>7</b>	<b>Indices and tables</b>	<b>15</b>
	<b>Python Module Index</b>	<b>17</b>
	<b>Index</b>	<b>19</b>



The MCP9808 is an awesome, high accuracy temperature sensor that communicates over I2C. Its available on [Adafruit](#) as a [breakout](#).



# CHAPTER 1

---

## Dependencies

---

This driver depends on:

- [Adafruit CircuitPython](#)
- [Bus Device](#)

Please ensure all dependencies are available on the CircuitPython filesystem. This is easily achieved by downloading the [Adafruit library and driver bundle](#).





## CHAPTER 2

---

### Installing from PyPI

---

On supported GNU/Linux systems like the Raspberry Pi, you can install the driver locally [from PyPI](#). To install for current user:

```
pip3 install adafruit-circuitpython-mcp9808
```

To install system-wide (this may be required in some cases):

```
sudo pip3 install adafruit-circuitpython-mcp9808
```

To install in a virtual environment in your current project:

```
mkdir project-name && cd project-name
python3 -m venv .env
source .env/bin/activate
pip3 install adafruit-circuitpython-mcp9808
```



## CHAPTER 3

---

### Usage Notes

---

Getting the temperature in Celsius is easy! First, import all of the pins from the board, busio for native I2C communication and the thermometer library itself.

```
from board import *
import busio
import adafruit_mcp9808
```

Next, initialize the I2C bus in a with statement so it always gets shut down ok. Then, construct the thermometer class:

```
# Do one reading
with busio.I2C(SCL, SDA) as i2c:
    t = adafruit_mcp9808.MCP9808(i2c)

# Finally, read the temperature property and print it out
print(t.temperature)
```



## CHAPTER 4

---

### Contributing

---

Contributions are welcome! Please read our [Code of Conduct](#) before contributing to help this project stay welcoming.



## CHAPTER 5

---

### Documentation

---

For information on building library documentation, please check out [this guide](#).





### 6.1 Simple test

Ensure your device works with this simple test.

Listing 1: examples/mcp9808\_simpletest.py

```
1 import time
2 import board
3 import busio
4 import adafruit_mcp9808
5
6 i2c_bus = busio.I2C(board.SCL, board.SDA)
7
8 # To initialise using the default address:
9 mcp = adafruit_mcp9808.MCP9808(i2c_bus)
10
11 # To initialise using a specified address:
12 # Necessary when, for example, connecting A0 to VDD to make address=0x19
13 # mcp = adafruit_mcp9808.MCP9808(i2c_bus, address=0x19)
14
15
16 while True:
17     tempC = mcp.temperature
18     tempF = tempC * 9 / 5 + 32
19     print("Temperature: {} C {} F ".format(tempC, tempF))
20     time.sleep(2)
```

### 6.2 adafruit\_mcp9808 - MCP9808 I2C Temperature Sensor

CircuitPython library to support MCP9808 high accuracy temperature sensor.

- Author(s): Scott Shawcroft

## 6.2.1 Implementation Notes

### Hardware:

- Adafruit MCP9808 High Accuracy I2C Temperature Sensor Breakout (Product ID: 1782)

### Software and Dependencies:

- Adafruit CircuitPython firmware (0.8.0+) for the ESP8622 and M0-based boards: <https://github.com/adafruit/circuitpython/releases>
- Adafruit's Bus Device library: [https://github.com/adafruit/Adafruit\\_CircuitPython\\_BusDevice](https://github.com/adafruit/Adafruit_CircuitPython_BusDevice)

### Notes:

1. Datasheet: <http://www.adafruit.com/datasheets/MCP9808.pdf>

```
class adafruit_mcp9808.MCP9808 (i2c_bus, address=24)  
    Interface to the MCP9808 temperature sensor.  
  
    temperature  
        Temperature in celsius. Read-only.
```

## CHAPTER 7

---

### Indices and tables

---

- `genindex`
- `modindex`
- `search`



### a

adafruit\_mcp9808, [13](#)



## A

`adafruit_mcp9808` (*module*), [13](#)

## M

`MCP9808` (*class in adafruit\_mcp9808*), [14](#)

## T

`temperature` (*adafruit\_mcp9808.MCP9808* *attribute*), [14](#)