

---

# **Adafruit VC0706 Library Documentation**

***Release 1.0***

**Tony DiCola**

**Jan 23, 2020**



---

## Contents

---

<b>1</b>	<b>Dependencies</b>	<b>3</b>
<b>2</b>	<b>Installing from PyPI</b>	<b>5</b>
<b>3</b>	<b>Usage Example</b>	<b>7</b>
<b>4</b>	<b>Contributing</b>	<b>9</b>
<b>5</b>	<b>Documentation</b>	<b>11</b>
<b>6</b>	<b>Table of Contents</b>	<b>13</b>
6.1	Simple test . . . . .	13
6.2	adafruit_vc0706 . . . . .	16
6.2.1	Implementation Notes . . . . .	17
<b>7</b>	<b>Indices and tables</b>	<b>19</b>
	<b>Python Module Index</b>	<b>21</b>
	<b>Index</b>	<b>23</b>



CircuitPython module for use with the [VC0706 serial TTL camera](#). Allows basic image capture and download of image data from the camera over a serial connection. See examples for demo of saving image to a SD card (must be wired up separately) or internally.



# CHAPTER 1

---

## Dependencies

---

This driver depends on:

- Adafruit CircuitPython

Please ensure all dependencies are available on the CircuitPython filesystem. This is easily achieved by downloading the Adafruit library and driver bundle.



# CHAPTER 2

---

## Installing from PyPI

---

On supported GNU/Linux systems like the Raspberry Pi, you can install the driver locally [from PyPI](#). To install for current user:

```
pip3 install adafruit-circuitpython-vc0706
```

To install system-wide (this may be required in some cases):

```
sudo pip3 install adafruit-circuitpython-vc0706
```

To install in a virtual environment in your current project:

```
mkdir project-name && cd project-name  
python3 -m venv .env  
source .env/bin/activate  
pip3 install adafruit-circuitpython-vc0706
```



# CHAPTER 3

---

## Usage Example

---

See examples/snapshot.py.



# CHAPTER 4

---

## Contributing

---

Contributions are welcome! Please read our [Code of Conduct](#) before contributing to help this project stay welcoming.



# CHAPTER 5

---

## Documentation

---

For information on building library documentation, please check out [this guide](#).



# CHAPTER 6

---

## Table of Contents

---

### 6.1 Simple test

Ensure your device works with this simple test.

Listing 1: examples/vc0706\_snapshot\_filesystem.py

```
1  """VC0706 image capture to local storage.  
2  You must wire up the VC0706 to a USB or hardware serial port.  
3  Primarily for use with Linux/Raspberry Pi but also can work with Mac/Windows"""\n4  
5  import time  
6  import busio  
7  import board  
8  import adafruit_vc0706  
9  
10 # Set this to the full path to the file name to save the captured image. WILL  
11 # →OVERWRITE!  
12 # CircuitPython internal filesystem configuration:  
13 IMAGE_FILE = '/image.jpg'  
14 # USB to serial adapter configuration:  
15 # IMAGE_FILE = 'image.jpg' # Full path to file name to save captured image. Will  
16 # →overwrite!  
17 # Raspberry Pi configuration:  
18 # IMAGE_FILE = '/home/pi/image.jpg' # Full path to file name to save image. Will  
19 # →overwrite!  
20  
21 # Create a serial connection for the VC0706 connection.  
22 uart = busio.UART(board.TX, board.RX, baudrate=115200, timeout=0.25)  
23 # Update the serial port name to match the serial connection for the camera!  
24 # For use with USB to serial adapter:  
25 # import serial  
26 # uart = serial.Serial("/dev/ttyUSB0", baudrate=115200, timeout=0.25)
```

(continues on next page)

(continued from previous page)

```
25 # For use with Raspberry Pi:  
26 # import serial  
27 # uart = serial.Serial("/dev/ttyS0", baudrate=115200, timeout=0.25)  
28  
29 # Setup VC0706 camera  
30 vc0706 = adafruit_vc0706.VC0706(uart)  
31  
32 # Print the version string from the camera.  
33 print('VC0706 version:')  
34 print(vc0706.version)  
35  
36 # Set the image size.  
37 vc0706.image_size = adafruit_vc0706.IMAGE_SIZE_640x480  
38 # Or set IMAGE_SIZE_320x240 or IMAGE_SIZE_160x120  
39  
40 # Note you can also read the property and compare against those values to  
41 # see the current size:  
42 size = vc0706.image_size  
43 if size == adafruit_vc0706.IMAGE_SIZE_640x480:  
44     print('Using 640x480 size image.')  
45 elif size == adafruit_vc0706.IMAGE_SIZE_320x240:  
46     print('Using 320x240 size image.')  
47 elif size == adafruit_vc0706.IMAGE_SIZE_160x120:  
48     print('Using 160x120 size image.')  
49  
50 # Take a picture.  
51 print('Taking a picture in 3 seconds...')  
52 time.sleep(3)  
53 print('SNAP!')  
54 if not vc0706.take_picture():  
55     raise RuntimeError('Failed to take picture!')  
56  
57 # Print size of picture in bytes.  
58 frame_length = vc0706.frame_length  
59 print('Picture size (bytes): {}'.format(frame_length))  
60  
61 # Open a file for writing (overwriting it if necessary).  
62 # This will write 50 bytes at a time using a small buffer.  
63 # You MUST keep the buffer size under 100!  
64 print('Writing image: {}'.format(IMAGE_FILE), end='', flush=True)  
65 stamp = time.monotonic()  
66 with open(IMAGE_FILE, 'wb') as outfile:  
67     wcount = 0  
68     while frame_length > 0:  
69         t = time.monotonic()  
70         # Compute how much data is left to read as the lesser of remaining bytes  
71         # or the copy buffer size (32 bytes at a time). Buffer size MUST be  
72         # a multiple of 4 and under 100. Stick with 32!  
73         to_read = min(frame_length, 32)  
74         copy_buffer = bytearray(to_read)  
75         # Read picture data into the copy buffer.  
76         if vc0706.read_picture_into(copy_buffer) == 0:  
77             raise RuntimeError('Failed to read picture frame data!')  
78         # Write the data to SD card file and decrement remaining bytes.  
79         outfile.write(copy_buffer)  
80         frame_length -= 32  
81         # Print a dot every 2k bytes to show progress.
```

(continues on next page)

(continued from previous page)

```

82     wcount += 1
83     if wcount >= 64:
84         print('.', end='', flush=True)
85         wcount = 0
86     print()
87     print('Finished in %.1f seconds!' % (time.monotonic() - stamp))

```

Listing 2: examples/vc0706\_snapshot\_simpletest.py

```

1  """VC0706 image capture to SD card demo.
2  You must wire up the VC0706 to the board's serial port, and a SD card holder
3  to the board's SPI bus. Use the Feather M0 Adalogger as it includes a SD
4  card holder pre-wired to the board--this sketch is setup to use the Adalogger!
5  In addition you MUST also install the following dependent SD card library:
6  https://github.com/adafruit/Adafruit_CircuitPython_SD
7  See the guide here for more details on using SD cards with CircuitPython:
8  https://learn.adafruit.com/micropython-hardware-sd-cards"""
9
10 import time
11
12 import board
13 import busio
14 import digitalio
15 import storage
16
17 import adafruit_sdcard
18 import adafruit_vc0706
19
20
21 # Configuration:
22 SD_CS_PIN = board.D10 # CS for SD card (SD_CS is for Feather Adalogger)
23 IMAGE_FILE = '/sd/image.jpg' # Full path to file name to save captured image.
24 # Will overwrite!
25
26 # Setup SPI bus (hardware SPI).
27 spi = busio.SPI(board.SCK, MOSI=board.MOSI, MISO=board.MISO)
28
29 # Setup SD card and mount it in the filesystem.
30 sd_cs = digitalio.DigitalInOut(SD_CS_PIN)
31 sdcard = adafruit_sdcard.SDCard(spi, sd_cs)
32 vfs = storage.VfsFat(sdcard)
33 storage.mount(vfs, '/sd')
34
35 # Create a serial connection for the VC0706 connection, speed is auto-detected.
36 uart = busio.UART(board.TX, board.RX, timeout=250)
37 # Setup VC0706 camera
38 vc0706 = adafruit_vc0706.VC0706(uart)
39
40 # Print the version string from the camera.
41 print('VC0706 version:')
42 print(vc0706.version)
43
44 # Set the baud rate to 115200 for fastest transfer (its the max speed)
45 vc0706.baudrate = 115200
46
47 # Set the image size.

```

(continues on next page)

(continued from previous page)

```
48 vc0706.image_size = adafruit_vc0706.IMAGE_SIZE_640x480 # Or set IMAGE_SIZE_320x240 or
49 #           # IMAGE_SIZE_160x120
50 # Note you can also read the property and compare against those values to
51 # see the current size:
52 size = vc0706.image_size
53 if size == adafruit_vc0706.IMAGE_SIZE_640x480:
54     print('Using 640x480 size image.')
55 elif size == adafruit_vc0706.IMAGE_SIZE_320x240:
56     print('Using 320x240 size image.')
57 elif size == adafruit_vc0706.IMAGE_SIZE_160x120:
58     print('Using 160x120 size image.')
59
60 # Take a picture.
61 print('Taking a picture in 3 seconds...')
62 time.sleep(3)
63 print('SNAP!')
64 if not vc0706.take_picture():
65     raise RuntimeError('Failed to take picture!')
66
67 # Print size of picture in bytes.
68 frame_length = vc0706.frame_length
69 print('Picture size (bytes): {}'.format(frame_length))
70
71 # Open a file for writing (overwriting it if necessary).
72 # This will write 50 bytes at a time using a small buffer.
73 # You MUST keep the buffer size under 100!
74 print('Writing image: {}'.format(IMAGE_FILE), end='')
75 with open(IMAGE_FILE, 'wb') as outfile:
76     wcount = 0
77     while frame_length > 0:
78         # Compute how much data is left to read as the lesser of remaining bytes
79         # or the copy buffer size (32 bytes at a time). Buffer size MUST be
80         # a multiple of 4 and under 100. Stick with 32!
81         to_read = min(frame_length, 32)
82         copy_buffer = bytearray(to_read)
83         # Read picture data into the copy buffer.
84         if vc0706.read_picture_into(copy_buffer) == 0:
85             raise RuntimeError('Failed to read picture frame data!')
86         # Write the data to SD card file and decrement remaining bytes.
87         outfile.write(copy_buffer)
88         frame_length -= 32
89         # Print a dot every 2k bytes to show progress.
90         wcount += 1
91         if wcount >= 64:
92             print('.', end='')
93             wcount = 0
94     print()
95     print('Finished!')
```

## 6.2 adafruit\_vc0706

VC0706 serial TTL camera module. Allows basic image capture and download of image data from the camera over a serial connection. See examples for demo of saving image to a SD card (must be wired up separately).

- Author(s): Tony DiCola

## 6.2.1 Implementation Notes

### Hardware:

- Adafruit TTL Serial JPEG Camera with NTSC Video (Product ID: 397)

### Software and Dependencies:

- Adafruit CircuitPython firmware for the ESP8622 and M0-based boards: <https://github.com/adafruit/circuitpython/releases>

**class** adafruit\_vc0706.**VC0706**(uart, \*, buffer\_size=100)

Driver for VC0706 serial TTL camera module. :param ~busio.UART uart: uart serial or compatible interface  
:param int buffer\_size: Receive buffer size

**baudrate**

Return the currently configured baud rate.

**frame\_length**

Return the length in bytes of the currently capture frame/picture.

**image\_size**

Get the current image size, will return a value of IMAGE\_SIZE\_640x480, IMAGE\_SIZE\_320x240, or IMAGE\_SIZE\_160x120.

**read\_picture\_into**(buf)

Read the next bytes of frame/picture data into the provided buffer. Returns the number of bytes written to the buffer (might be less than the size of the buffer). Buffer MUST be a multiple of 4 and 100 or less. Suggested buffer size is 32.

**take\_picture()**

Tell the camera to take a picture. Returns True if successful.

**version**

Return camera version byte string.



# CHAPTER 7

---

## Indices and tables

---

- genindex
- modindex
- search



---

## Python Module Index

---

**a**

`adafruit_vc0706`, 16



---

## Index

---

### A

`adafruit_vc0706` (*module*), 16

### B

`baudrate` (*adafruit\_vc0706.VC0706 attribute*), 17

### F

`frame_length` (*adafruit\_vc0706.VC0706 attribute*),  
17

### I

`image_size` (*adafruit\_vc0706.VC0706 attribute*), 17

### R

`read_picture_into()` (*adafruit\_vc0706.VC0706 method*), 17

### T

`take_picture()` (*adafruit\_vc0706.VC0706 method*),  
17

### V

`VC0706` (*class in adafruit\_vc0706*), 17

`version` (*adafruit\_vc0706.VC0706 attribute*), 17