
AdafruitAPDS9960 Library Documentation

Release 1.0

Michael McWethy

Mar 16, 2018

Contents

1	Dependencies	3
2	Usage Example	5
2.1	Hardware Set-up	5
2.2	Basics	5
2.3	Gestures	5
2.4	Color Measurement	6
2.5	Proximity Detection	6
3	Contributing	7
4	Building locally	9
4.1	Sphinx documentation	9
5	Table of Contents	11
5.1	Simple test	11
5.2	colorutility	12
6	Indices and tables	15
	Python Module Index	17

The APDS9960 is a specialize chip that detects hand gestures, proximity detection and ambient light color over I2C. Its available on [Adafruit](#) as a breakout.

CHAPTER 1

Dependencies

This driver depends on:

- Adafruit CircuitPython

Please ensure all dependencies are available on the CircuitPython filesystem. This is easily achieved by downloading the Adafruit library and driver bundle.

CHAPTER 2

Usage Example

2.1 Hardware Set-up

Connect Vin to 3.3 V or 5 V power source, GND to ground, SCL and SDA to the appropriate pins.

2.2 Basics

Of course, you must import i2c bus device, board pins, and the library:

```
from board import SCL, SDA, A1
from adafruit_apds9960.apds9960 import APDS9960
import busio
import digitalio
```

To set-up the device to gather data, initialize the I2CDevice using SCL and SDA pins. Then initialize the library. Optionally provide an interrupt pin for proximity detection.

```
int_pin = digitalio.DigitalInOut(A1)
i2c = busio.I2C(SCL, SDA)
apds = APDS9960(i2c, interrupt_pin=int_pin)
```

2.3 Gestures

To get a gesture, see if a gesture is available first, then get the gesture Code

```
gesture = apds.gesture()
if gesture == 1:
    print("up")
if gesture == 2:
    print("down")
```

```
if gesture == 3:  
    print("left")  
if gesture == 4:  
    print("right")
```

2.4 Color Measurement

To get a color measure, enable color measures, wait for color data, then get the color data.

```
apds.enable_color = True  
  
while not apds.color_data_ready:  
    time.sleep(0.005)  
  
r, g, b, c = apds.color_data  
print("r: {}, g: {}, b: {}, c: {}".format(r, g, b, c))
```

2.5 Proximity Detection

To check for a object in proximity, see if a gesture is available first, then get the gesture Code

```
apds.enable_proximity = True  
  
# set the interrupt threshold to fire when proximity reading goes above 175  
apds.proximity_interrupt_threshold = (0, 175)  
  
# enable the proximity interrupt  
apds.enable_proximity_interrupt = True  
  
while True:  
    if not interrupt_pin.value:  
        print(apds.proximity())  
  
    # clear the interrupt  
    apds.clear_interrupt()
```

CHAPTER 3

Contributing

Contributions are welcome! Please read our [Code of Conduct](#) before contributing to help this project stay welcoming.

CHAPTER 4

Building locally

To build this library locally you'll need to install the `circuitpython-travis-build-tools` package.

Once installed, make sure you are in the virtual environment:

Then run the build:

4.1 Sphinx documentation

Sphinx is used to build the documentation based on rST files and comments in the code. First, install dependencies (feel free to reuse the virtual environment from above):

```
python3 -m venv .env
source .env/bin/activate
pip install Sphinx sphinx-rtd-theme
```

Now, once you have the virtual environment activated:

```
cd docs
sphinx-build -E -W -b html . _build/html
```

This will output the documentation to `docs/_build/html`. Open the `index.html` in your browser to view them. It will also (due to `-W`) error out on any warning like Travis will. This is a good way to locally verify it will pass.

CHAPTER 5

Table of Contents

5.1 Simple test

Ensure your device works with this simple test.

Listing 5.1: examples/apds9960_color_simpletest.py

```
1 import time
2 import board
3 import busio
4 import digitalio
5 from adafruit_apds9960.apds9960 import APDS9960
6 from adafruit_apds9960 import colorutility
7
8 i2c = busio.I2C(board.SCL, board.SDA)
9 int_pin = digitalio.DigitalInOut(board.A2)
10 apds = APDS9960(i2c)
11 apds.enable_color = True
12
13
14 while True:
15     #create some variables to store the color data in
16
17     #wait for color data to be ready
18     while not apds.color_data_ready:
19         time.sleep(0.005)
20
21
22     #get the data and print the different channels
23     r, g, b, c = apds.color_data
24     print("red: ", r)
25     print("green: ", g)
26     print("blue: ", b)
27     print("clear: ", c)
28
```

```
29     print("color temp {}".format(colorutility.calculate_color_temperature(r, g, b)))
30     print("light lux {}".format(colorutility.calculate_lux(r, g, b)))
31     time.sleep(0.5)
```

Listing 5.2: examples/apds9960_gesture_simpletest.py

```
1  from board import SCL, SDA
2  import busio
3  from adafruit_apds9960.apds9960 import APDS9960
4
5  i2c = busio.I2C(SCL, SDA)
6
7  apds = APDS9960(i2c)
8  apds.enable_proximity = True
9  apds.enable_gesture = True
10
11 while True:
12     gesture = apds.gesture()
13
14     if gesture == 0x01:
15         print("up")
16     elif gesture == 0x02:
17         print("down")
18     elif gesture == 0x03:
19         print("left")
20     elif gesture == 0x04:
21         print("right")
```

Listing 5.3: examples/apds9960_proximity_simpletest.py

```
1  import board
2  import busio
3  import digitalio
4  from adafruit_apds9960.apds9960 import APDS9960
5
6  i2c = busio.I2C(board.SCL, board.SDA)
7  int_pin = digitalio.DigitalInOut(board.A1)
8  apds = APDS9960(i2c, interrupt_pin=int_pin)
9
10 apds.enable_proximity = True
11 apds.proximity_interrupt_threshold = (0, 175)
12 apds.enable_proximity_interrupt = True
13
14 while True:
15     # print the proximity reading when the interrupt pin goes low
16     if not int_pin.value:
17         print(apds.proximity())
18
19     # clear the interrupt
20     apds.clear_interrupt()
```

5.2 colorutility

Helper functions for color calculations

- Author(s): Michael McWethy

`adafruit_apds9960.colorutility.calculate_color_temperature(r, g, b)`
Converts the raw R/G/B values to color temperature in degrees Kelvin

`adafruit_apds9960.colorutility.calculate_lux(r, g, b)`
Calculate ambient light values

CHAPTER 6

Indices and tables

- genindex
- modindex
- search

Python Module Index

a

adafruit_apds9960.colorutility, 12

Index

A

`adafruit_apds9960.colorutility` (module), [12](#)

C

`calculate_color_temperature()` (in module
 `adafruit_apds9960.colorutility`), [13](#)

`calculate_lux()` (in module
 `adafruit_apds9960.colorutility`), [13](#)