

---

# AdafruitFocalTouch Library Documentation

*Release 1.0*

**ladyada**

**Apr 10, 2020**



---

## Contents

---

|          |                                |           |
|----------|--------------------------------|-----------|
| <b>1</b> | <b>Dependencies</b>            | <b>3</b>  |
| <b>2</b> | <b>Installing from PyPI</b>    | <b>5</b>  |
| <b>3</b> | <b>Usage Example</b>           | <b>7</b>  |
| <b>4</b> | <b>Contributing</b>            | <b>9</b>  |
| <b>5</b> | <b>Documentation</b>           | <b>11</b> |
| <b>6</b> | <b>Table of Contents</b>       | <b>13</b> |
| 6.1      | Simple tests . . . . .         | 13        |
| 6.2      | adafruit_focaltouch . . . . .  | 14        |
| 6.2.1    | Implementation Notes . . . . . | 14        |
| <b>7</b> | <b>Indices and tables</b>      | <b>17</b> |
|          | <b>Python Module Index</b>     | <b>19</b> |
|          | <b>Index</b>                   | <b>21</b> |



CircuitPython driver for common low-cost FocalTech capacitive touch chips. Currently supports FT6206 & FT6236



# CHAPTER 1

---

## Dependencies

---

This driver depends on:

- [Adafruit CircuitPython](#)
- [Bus Device](#)

Please ensure all dependencies are available on the CircuitPython filesystem. This is easily achieved by downloading the [Adafruit library and driver bundle](#).





## CHAPTER 2

---

### Installing from PyPI

---

On supported GNU/Linux systems like the Raspberry Pi, you can install the driver locally [from PyPI](#). To install for current user:

```
pip3 install adafruit-circuitpython-focaltouch
```

To install system-wide (this may be required in some cases):

```
sudo pip3 install adafruit-circuitpython-focaltouch
```

To install in a virtual environment in your current project:

```
mkdir project-name && cd project-name
python3 -m venv .env
source .env/bin/activate
pip3 install adafruit-circuitpython-focaltouch
```



## CHAPTER 3

---

### Usage Example

---

```
import time
import board
import busio
import adafruit_focaltouch

# Create library object (named "ft") using a Bus I2C port
i2c = busio.I2C(board.SCL, board.SDA)

ft = adafruit_focaltouch.Adafruit_FocalTouch(i2c, debug=False)

while True:
    # if the screen is being touched print the touches
    if ft.touched:
        print(ft.touches)
    else:
        print('no touch')

    time.sleep(.15)
```



## CHAPTER 4

---

### Contributing

---

Contributions are welcome! Please read our [Code of Conduct](#) before contributing to help this project stay welcoming.



## CHAPTER 5

---

### Documentation

---

For information on building library documentation, please check out [this guide](#).





## 6.1 Simple tests

Ensure your device works with these simple tests.

Listing 1: examples/focaltouch\_print\_touches.py

```
1  """
2  Example for getting touch data from an FT6206 or FT6236 capacitive
3  touch driver, over I2C
4  """
5
6  import time
7  import busio
8  import board
9  import adafruit_focaltouch
10
11  # Create library object (named "ft") using a Bus I2C port
12  i2c = busio.I2C(board.SCL, board.SDA)
13
14  ft = adafruit_focaltouch.Adafruit_FocalTouch(i2c, debug=False)
15
16  while True:
17      # if the screen is being touched print the touches
18      if ft.touched:
19          print(ft.touches)
20      else:
21          print("no touch")
22
23      time.sleep(0.15)
```

Listing 2: examples/focaltouch\_paint\_simpletest.py

```
1 """
2 Simple painting demo that draws on an Adafruit capacitive touch shield with
3 ILI9341 display and FT6206 captouch driver
4 """
5
6 import busio
7 import board
8 import digitalio
9 import adafruit_focaltouch
10 from adafruit_rgb_display import ili9341, color565
11
12 # Create library object using our Bus I2C & SPI port
13 i2c = busio.I2C(board.SCL, board.SDA)
14 spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)
15
16 # Adafruit Metro M0 + 2.8" Capacitive touch shield
17 cs_pin = digitalio.DigitalInOut(board.D10)
18 dc_pin = digitalio.DigitalInOut(board.D9)
19
20 # Initialize display
21 display = ili9341.ILI9341(spi, cs=cs_pin, dc=dc_pin)
22 # Fill with black!
23 display.fill(color565(0, 0, 0))
24
25 ft = adafruit_focaltouch.Adafruit_FocalTouch(i2c)
26
27 while True:
28     if ft.touched:
29         ts = ft.touches
30         point = ts[0] # the shield only supports one point!
31         # perform transformation to get into display coordinate system!
32         y = 320 - point["y"]
33         x = 240 - point["x"]
34         display.fill_rectangle(x - 2, y - 2, 4, 4, color565(255, 255, 255))
```

## 6.2 adafruit\_focaltouch

CircuitPython driver for common low-cost FocalTech capacitive touch chips. Currently supports FT6206 & FT6236.

- Author(s): ladyada

### 6.2.1 Implementation Notes

#### Hardware:

- Adafruit 2.8" TFT LCD with Cap Touch Breakout Board w/MicroSD Socket (Product ID: 2090)
- Adafruit 2.8" TFT Touch Shield for Arduino w/Capacitive Touch (Product ID: 1947)

#### Software and Dependencies:

- Adafruit CircuitPython firmware for the ESP8622 and M0-based boards: <https://github.com/adafruit/circuitpython/releases>

- Adafruit's Bus Device library (when using I2C/SPI): [https://github.com/adafruit/Adafruit\\_CircuitPython\\_BusDevice](https://github.com/adafruit/Adafruit_CircuitPython_BusDevice)

**class** adafruit\_focaltouch.**Adafruit\_FocalTouch** (*i2c*, *address=56*, *debug=False*)

A driver for the FocalTech capacitive touch sensor.

**touched**

Returns the number of touches currently detected

**touches**

Returns a list of touchpoint dicts, with 'x' and 'y' containing the touch coordinates, and 'id' as the touch # for multitouch tracking



## CHAPTER 7

---

### Indices and tables

---

- `genindex`
- `modindex`
- `search`



### a

`adafruit_focaltouch`, [14](#)





## A

`Adafruit_FocalTouch` (class in *adafruit\_focaltouch*), 15  
`adafruit_focaltouch` (module), 14

## T

`touched` (*adafruit\_focaltouch.Adafruit\_FocalTouch* attribute), 15  
`touches` (*adafruit\_focaltouch.Adafruit\_FocalTouch* attribute), 15