

---

# **Adafruit FXAS21002C Library Documentation**

***Release 1.0***

**Tony DiCola**

**Mar 02, 2021**



---

## Contents

---

<b>1</b>	<b>Dependencies</b>	<b>3</b>
<b>2</b>	<b>Installing from PyPI</b>	<b>5</b>
<b>3</b>	<b>Usage Example</b>	<b>7</b>
<b>4</b>	<b>Contributing</b>	<b>9</b>
<b>5</b>	<b>Documentation</b>	<b>11</b>
<b>6</b>	<b>Table of Contents</b>	<b>13</b>
6.1	Simple test . . . . .	13
6.2	adafruit_fxas21002c . . . . .	14
6.2.1	Implementation Notes . . . . .	14
<b>7</b>	<b>Indices and tables</b>	<b>15</b>
	<b>Python Module Index</b>	<b>17</b>
	<b>Index</b>	<b>19</b>



CircuitPython module for the NXP FXAS21002C gyroscope.



# CHAPTER 1

---

## Dependencies

---

This driver depends on:

- [Adafruit CircuitPython](#)
- [Bus Device](#)

Please ensure all dependencies are available on the CircuitPython filesystem. This is easily achieved by downloading the [Adafruit library and driver bundle](#).





## CHAPTER 2

---

### Installing from PyPI

---

On supported GNU/Linux systems like the Raspberry Pi, you can install the driver locally [from PyPI](#). To install for current user:

```
pip3 install adafruit-circuitpython-fxas21002c
```

To install system-wide (this may be required in some cases):

```
sudo pip3 install adafruit-circuitpython-fxas21002c
```

To install in a virtual environment in your current project:

```
mkdir project-name && cd project-name
python3 -m venv .env
source .env/bin/activate
pip3 install adafruit-circuitpython-fxas21002c
```



## CHAPTER 3

---

### Usage Example

---

```
import time
import board
import busio
import adafruit_fxas21002c

i2c = busio.I2C(board.SCL, board.SDA)
sensor = adafruit_fxas21002c.FXAS21002C(i2c)

while True:
    gyro_x, gyro_y, gyro_z = sensor.gyroscope
    print('Gyroscope (radians/s): ({0:0.3f}, {1:0.3f}, {2:0.3f})'.format(gyro_x, ↵
    ↵gyro_y, gyro_z))
    time.sleep(1.0)
```



## CHAPTER 4

---

### Contributing

---

Contributions are welcome! Please read our [Code of Conduct](#) before contributing to help this project stay welcoming.



## CHAPTER 5

---

### Documentation

---

For information on building library documentation, please check out [this guide](#).





---

Table of Contents

---

## 6.1 Simple test

Ensure your device works with this simple test.

Listing 1: examples/fxas21002c\_simpletest.py

```
1  # SPDX-FileCopyrightText: 2021 ladyada for Adafruit Industries
2  # SPDX-License-Identifier: MIT
3
4  # Simple demo of the FXAS21002C gyroscope.
5  # Will print the gyroscope values every second.
6  import time
7
8  import board
9  import busio
10
11  import adafruit_fxas21002c
12
13
14  # Initialize I2C bus and device.
15  i2c = busio.I2C(board.SCL, board.SDA)
16  sensor = adafruit_fxas21002c.FXAS21002C(i2c)
17  # Optionally create the sensor with a different gyroscope range (the
18  # default is 250 DPS, but you can use 500, 1000, or 2000 DPS values):
19  # sensor = adafruit_fxas21002c.FXAS21002C(i2c, gyro_range=adafruit_fxas21002c.GYRO_
20  ↪ RANGE_500DPS)
21  # sensor = adafruit_fxas21002c.FXAS21002C(i2c, gyro_range=adafruit_fxas21002c.GYRO_
22  ↪ RANGE_1000DPS)
23  # sensor = adafruit_fxas21002c.FXAS21002C(i2c, gyro_range=adafruit_fxas21002c.GYRO_
24  ↪ RANGE_2000DPS)
25
26  # Main loop will read the gyroscope values every second and print them out.
27  while True:
```

(continues on next page)

(continued from previous page)

```
25     # Read gyroscope.
26     gyro_x, gyro_y, gyro_z = sensor.gyroscope
27     # Print values.
28     print(
29         "Gyroscope (radians/s): ({0:0.3f}, {1:0.3f}, {2:0.3f})".format(
30             gyro_x, gyro_y, gyro_z
31         )
32     )
33     # Delay for a second.
34     time.sleep(1.0)
```

## 6.2 adafruit\_fxas21002c

CircuitPython module for the NXP FXAS21002C gyroscope. Based on the driver from: [https://github.com/adafruit/Adafruit\\_FXAS21002C](https://github.com/adafruit/Adafruit_FXAS21002C)

See examples/simpletest.py for a demo of the usage.

- Author(s): Tony DiCola

### 6.2.1 Implementation Notes

#### Hardware:

- Adafruit Precision NXP 9-DOF Breakout Board - FXOS8700 + FXAS21002 (Product ID: 3463)

#### Software and Dependencies:

- Adafruit CircuitPython firmware (2.2.0+) for the ESP8622 and M0-based boards: <https://github.com/adafruit/circuitpython/releases>
- Adafruit's Bus Device library: [https://github.com/adafruit/Adafruit\\_CircuitPython\\_BusDevice](https://github.com/adafruit/Adafruit_CircuitPython_BusDevice)

**class** `adafruit_fxas21002c.FXAS21002C` (*i2c*, *address=33*, *gyro\_range=250*)

Driver for the NXP FXAS21002C gyroscope.

#### **gyroscope**

Read the gyroscope value and return its X, Y, Z axis values as a 3-tuple in radians/second.

#### **read\_raw()**

Read the raw gyroscope readings. Returns a 3-tuple of X, Y, Z axis 16-bit signed values. If you want the gyroscope values in friendly units consider using the `gyroscope` property!

## CHAPTER 7

---

### Indices and tables

---

- `genindex`
- `modindex`
- `search`



### a

`adafruit_fxas21002c`, [14](#)



## A

`adafruit_fxas21002c` (*module*), [14](#)

## F

`FXAS21002C` (*class in adafruit\_fxas21002c*), [14](#)

## G

`gyroscope` (*adafruit\_fxas21002c.FXAS21002C* *attribute*), [14](#)

## R

`read_raw()` (*adafruit\_fxas21002c.FXAS21002C* *method*), [14](#)