
Adafruit LSM9DS0 Library Documentation

Release 1.0

Tony DiCola

Jul 09, 2020

Contents

1	Dependencies	3
2	Installing from PyPI	5
3	Usage Example	7
4	Contributing	9
5	Documentation	11
6	Table of Contents	13
6.1	Simple test	13
6.2	adafruit_lsm9ds0	14
6.2.1	Implementation Notes	14
7	Indices and tables	17
	Python Module Index	19
	Index	21

CircuitPython module for the LSM9DS0 accelerometer, magnetometer, gyroscope.

CHAPTER 1

Dependencies

This driver depends on:

- Adafruit CircuitPython
- Bus Device

Please ensure all dependencies are available on the CircuitPython filesystem. This is easily achieved by downloading the [Adafruit library and driver bundle](#).

CHAPTER 2

Installing from PyPI

On supported GNU/Linux systems like the Raspberry Pi, you can install the driver locally [from PyPI](#). To install for current user:

```
pip3 install adafruit-circuitpython-lsm9ds0
```

To install system-wide (this may be required in some cases):

```
sudo pip3 install adafruit-circuitpython-lsm9ds0
```

To install in a virtual environment in your current project:

```
mkdir project-name && cd project-name
python3 -m venv .env
source .env/bin/activate
pip3 install adafruit-circuitpython-lsm9ds0
```


CHAPTER 3

Usage Example

```
import time
import board
import busioimport adafruit_lsm9ds0

i2c = busio.I2C(board.SCL, board.SDA)
sensor = adafruit_lsm9ds0.LSM9DS0_I2C(i2c)

while True:
    accel_x, accel_y, accel_z = sensor.acceleration
    mag_x, mag_y, mag_z = sensor.magnetic
    gyro_x, gyro_y, gyro_z = sensor.gyro
    temp = sensor.temperature
    print('Acceleration (m/s^2): ({0:0.3f},{1:0.3f},{2:0.3f})'.format(accel_x, accel_y, accel_z))
    print('Magnetometer (gauss): ({0:0.3f},{1:0.3f},{2:0.3f})'.format(mag_x, mag_y, mag_z))
    print('Gyroscope (degrees/sec): ({0:0.3f},{1:0.3f},{2:0.3f})'.format(gyro_x, gyro_y, gyro_z))
    print('Temperature: {0:0.3f}C'.format(temp))
    time.sleep(1.0)
```


CHAPTER 4

Contributing

Contributions are welcome! Please read our [Code of Conduct](#) before contributing to help this project stay welcoming.

CHAPTER 5

Documentation

For information on building library documentation, please check out [this guide](#).

CHAPTER 6

Table of Contents

6.1 Simple test

Ensure your device works with this simple test.

Listing 1: examples/lsm9ds0_simpletest.py

```
1 # Simple demo of the LSM9DS0 accelerometer, magnetometer, gyroscope.
2 # Will print the acceleration, magnetometer, and gyroscope values every second.
3 import time
4
5 import board
6 import busio
7
8 # import digitalio # Used with SPI
9
10 import adafruit_lsm9ds0
11
12 # I2C connection:
13 i2c = busio.I2C(board.SCL, board.SDA)
14 sensor = adafruit_lsm9ds0.LSM9DS0_I2C(i2c)
15
16 # SPI connection:
17 # from digitalio import DigitalInOut, Direction
18 # spi = busio.SPI(board.SCK, board.MOSI, board.MISO)
19 # gcs = DigitalInOut(board.D5)
20 # xmcs = DigitalInOut(board.D6)
21 # sensor = adafruit_lsm9ds0.LSM9DS0_SPI(spi, xmcs, gcs)
22
23 # Main loop will read the acceleration, magnetometer, gyroscope, Temperature
24 # values every second and print them out.
25 while True:
26     # Read acceleration, magnetometer, gyroscope, temperature.
27     accel_x, accel_y, accel_z = sensor.acceleration
```

(continues on next page)

(continued from previous page)

```
28     mag_x, mag_y, mag_z = sensor.magnetic
29     gyro_x, gyro_y, gyro_z = sensor.gyro
30     temp = sensor.temperature
31     # Print values.
32     print(
33         "Acceleration (m/s^2): ({0:0.3f}, {1:0.3f}, {2:0.3f})".format(
34             accel_x, accel_y, accel_z
35         )
36     )
37     print(
38         "Magnetometer (gauss): ({0:0.3f}, {1:0.3f}, {2:0.3f})".format(mag_x, mag_y, mag_
39         z)
39     )
40     print(
41         "Gyroscope (degrees/sec): ({0:0.3f}, {1:0.3f}, {2:0.3f})".format(
42             gyro_x, gyro_y, gyro_z
43         )
44     )
45     print("Temperature: {0:0.3f}C".format(temp))
46     # Delay for a second.
47     time.sleep(1.0)
```

6.2 adafruit_lsm9ds0

CircuitPython module for the LSM9DS0 accelerometer, magnetometer, gyroscope. Based on the driver from: https://github.com/adafruit/Adafruit_LSM9DS0

See examples/simpletest.py for a demo of the usage.

- Author(s): Tony DiCola

6.2.1 Implementation Notes

Hardware:

- Adafruit 9-DOF Accel/Mag/Gyro+Temp Breakout Board - LSM9DS0 (Product ID: 2021)
- FLORA 9-DOF Accelerometer/Gyroscope/Magnetometer - LSM9DS0 (Product ID: 2020)

Software and Dependencies:

- Adafruit CircuitPython firmware for the ESP8622 and M0-based boards: <https://github.com/adafruit/circuitpython/releases>
- Adafruit's Bus Device library: https://github.com/adafruit/Adafruit_CircuitPython_BusDevice

class adafruit_lsm9ds0.LSM9DS0

Driver for the LSM9DS0 accelerometer, magnetometer, gyroscope.

accel_range

The accelerometer range. Must be a value of: - ACCEL RANGE_2G - ACCEL RANGE_4G - ACCEL RANGE_6G - ACCEL RANGE_8G - ACCEL RANGE_16G

acceleration

The accelerometer X, Y, Z axis values as a 3-tuple of m/s² values.

gyro

The gyroscope X, Y, Z axis values as a 3-tuple of degrees/second values.

gyro_scale

The gyroscope scale. Must be a value of: - GYROSCALE_245DPS - GYROSCALE_500DPS - GYROSCALE_2000DPS

mag_gain

The magnetometer gain. Must be a value of: - MAGGAIN_2GAUSS - MAGGAIN_4GAUSS - MAGGAIN_8GAUSS - MAGGAIN_12GAUSS

magnetic

The magnetometer X, Y, Z axis values as a 3-tuple of gauss values.

read_accel_raw()

Read the raw accelerometer sensor values and return it as a 3-tuple of X, Y, Z axis values that are 16-bit unsigned values. If you want the acceleration in nice units you probably want to use the accelerometer property!

read_gyro_raw()

Read the raw gyroscope sensor values and return it as a 3-tuple of X, Y, Z axis values that are 16-bit unsigned values. If you want the gyroscope in nice units you probably want to use the gyroscope property!

read_mag_raw()

Read the raw magnetometer sensor values and return it as a 3-tuple of X, Y, Z axis values that are 16-bit unsigned values. If you want the magnetometer in nice units you probably want to use the magnetometer property!

read_temp_raw()

Read the raw temperature sensor value and return it as a 16-bit unsigned value. If you want the temperature in nice units you probably want to use the temperature property!

temperature

The temperature of the sensor in degrees Celsius.

class adafruit_lsm9ds0.LSM9DS0_I2C(i2c)

Driver for the LSM9DS0 connected over I2C.

class adafruit_lsm9ds0.LSM9DS0_SPI(spi, xmcs, gcs)

Driver for the LSM9DS0 connected over SPI.

CHAPTER 7

Indices and tables

- genindex
- modindex
- search

Python Module Index

a

[adafruit_lsm9ds0](#), 14

Index

A

accel_range (*adafruit_lsm9ds0.LSM9DS0 attribute*),
 14
acceleration (*adafruit_lsm9ds0.LSM9DS0 attribute*), 14
adafruit_lsm9ds0 (*module*), 14

G

gyro (*adafruit_lsm9ds0.LSM9DS0 attribute*), 14
gyro_scale (*adafruit_lsm9ds0.LSM9DS0 attribute*),
 15

L

LSM9DS0 (*class in adafruit_lsm9ds0*), 14
LSM9DS0_I2C (*class in adafruit_lsm9ds0*), 15
LSM9DS0_SPI (*class in adafruit_lsm9ds0*), 15

M

mag_gain (*adafruit_lsm9ds0.LSM9DS0 attribute*), 15
magnetic (*adafruit_lsm9ds0.LSM9DS0 attribute*), 15

R

read_accel_raw () (*adafruit_lsm9ds0.LSM9DS0 method*), 15
read_gyro_raw () (*adafruit_lsm9ds0.LSM9DS0 method*), 15
read_mag_raw () (*adafruit_lsm9ds0.LSM9DS0 method*), 15
read_temp_raw () (*adafruit_lsm9ds0.LSM9DS0 method*), 15

T

temperature (*adafruit_lsm9ds0.LSM9DS0 attribute*),
 15