
Adafruit MPR121 Library Documentation

Release 1.0

Tony DiCola

Jan 22, 2021

Contents

1	Dependencies	3
2	Installing from PyPI	5
3	Usage Example	7
4	Contributing	9
5	Documentation	11
6	Table of Contents	13
6.1	Simple test	13
6.2	adafruit_mpr121	15
6.2.1	Implementation Notes	15
7	Indices and tables	17
	Python Module Index	19
	Index	21

Adafruit CircuitPython module for the MPR121 capacitive touch breakout board.

CHAPTER 1

Dependencies

This driver depends on:

- Adafruit CircuitPython
- Bus Device

Please ensure all dependencies are available on the CircuitPython filesystem. This is easily achieved by downloading the [Adafruit library and driver bundle](#).

CHAPTER 2

Installing from PyPI

On supported GNU/Linux systems like the Raspberry Pi, you can install the driver locally [from PyPI](#). To install for current user:

```
pip3 install adafruit-circuitpython-mpr121
```

To install system-wide (this may be required in some cases):

```
sudo pip3 install adafruit-circuitpython-mpr121
```

To install in a virtual environment in your current project:

```
mkdir project-name && cd project-name  
python3 -m venv .env  
source .env/bin/activate  
pip3 install adafruit-circuitpython-mpr121
```


CHAPTER 3

Usage Example

See usage in the examples/mpr121_simpletest.py file.

CHAPTER 4

Contributing

Contributions are welcome! Please read our [Code of Conduct](#) before contributing to help this project stay welcoming.

CHAPTER 5

Documentation

For information on building library documentation, please check out [this guide](#).

CHAPTER 6

Table of Contents

6.1 Simple test

Ensure your device works with this simple test.

Listing 1: examples/mpr121_simpletest.py

```
1 # SPDX-FileCopyrightText: 2017 Tony DiCola for Adafruit Industries
2 # SPDX-License-Identifier: MIT
3
4 # Simple test of the MPR121 capacitive touch sensor library.
5 # Will print out a message when any of the 12 capacitive touch inputs of the
6 # board are touched. Open the serial REPL after running to see the output.
7 # Author: Tony DiCola
8 import time
9 import board
10 import busio
11
12 # Import MPR121 module.
13 import adafruit_mpr121
14
15 # Create I2C bus.
16 i2c = busio.I2C(board.SCL, board.SDA)
17
18 # Create MPR121 object.
19 mpr121 = adafruit_mpr121.MPR121(i2c)
20
21 # Note you can optionally change the address of the device:
22 # mpr121 = adafruit_mpr121.MPR121(i2c, address=0x91)
23
24 # Loop forever testing each input and printing when they're touched.
25 while True:
26     # Loop through all 12 inputs (0-11).
27     for i in range(12):
```

(continues on next page)

(continued from previous page)

```
28     # Call is_touched and pass it then number of the input. If it's touched
29     # it will return True, otherwise it will return False.
30     if mpr121[i].value:
31         print("Input {} touched!".format(i))
32         time.sleep(0.25) # Small delay to keep from spamming output messages.
```

Listing 2: examples/mpr121_piano.py

```
1  # SPDX-FileCopyrightText: 2017 Tony DiCola, Carter Nelson for Adafruit Industries
2  # SPDX-License-Identifier: MIT
3
4  # MPR121 piano demo.
5  # Listens to the first 7 inputs of the MPR121 and plays a middle scale note
6  # when an input is touched. Note only one note is played at a time!
7  # For use with microcontrollers or computers with PWM support only!
8
9
10 import board
11 import busio
12 import pulseio
13
14 # Import MPR121 module.
15 import adafruit_mpr121
16
17
18 # Configure PWM buzzer and other state:
BUZZER_PIN = board.D9
TONE_ON_DUTY = 2 ** 15 # Duty cycle of tone when turned on, a square wave.
TONE_OFF_DUTY = 0 # Duty cycle of tone when turned off, 0 or no signal.
NOTE_FREQS = [
    261, # Input 0 = 261 hz = middle C
    294, # Input 1 = middle D
    329, # Input 2 = middle E
    349, # Input 3 = middle F
    392, # Input 4 = middle G
    440, # Input 5 = middle A
    493, # Input 6 = middle B
    0, # Input 7 = nothing (set to a frequency in hertz!)
    0, # Input 8
    0, # Input 9
    0, # Input 10
    0,
] # Input 11
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
```

(continues on next page)

(continued from previous page)

```

49     BUZZER_PIN, duty_cycle=TONE_OFF_DUTY, frequency=440, variable_frequency=True
50 )
51 # pylint: disable-msg=no-member
52
53 last_note = None
54 while True:
55     # Get touched state for all pins
56     touched = mpr121.touched_pins
57     # If no pins are touched, be quiet
58     if True not in touched:
59         last_note = None
60         buzzer.duty_cycle = TONE_OFF_DUTY
61         continue
62     # Get index of touched pin
63     note = touched.index(True)
64     # Play note if pin is different and has a defined note
65     if note != last_note and NOTE_FREQS[note] != 0:
66         last_note = note
67         buzzer.frequency = NOTE_FREQS[note]
68         buzzer.duty_cycle = TONE_ON_DUTY

```

6.2 adafruit_mpr121

CircuitPython driver for the MPR121 capacitive touch breakout board.

See usage in the examples/simpletest.py file.

- Author(s): Tony DiCola

6.2.1 Implementation Notes

Hardware:

- Adafruit 12-Key Capacitive Touch Sensor Breakout - MPR121 (Product ID: 1982)
- Adafruit 12 x Capacitive Touch Shield for Arduino - MPR121 (Product ID: 2024)

Software and Dependencies:

- Adafruit CircuitPython firmware for the ESP8622 and M0-based boards: <https://github.com/adafruit/circuitpython/releases>
- Adafruit's Bus Device library: https://github.com/adafruit/Adafruit_CircuitPython_BusDevice

```
class adafruit_mpr121.MPR121(i2c, address=90)
    Driver for the MPR121 capacitive touch breakout board.
```

`baseline_data(pin)`

Return baseline data register value for the provided pin (0-11). Useful for debugging.

`filtered_data(pin)`

Return filtered data register value for the provided pin (0-11). Useful for debugging.

`is_touched(pin)`

Return True if the specified pin is being touched, otherwise returns False.

reset()

Reset the MPR121 into a default state ready to detect touch inputs.

touched()

Return touch state of all pins as a 12-bit value where each bit represents a pin, with a value of 1 being touched and 0 not being touched.

touched_pins

A tuple of touched state for all pins.

class adafruit_mpr121.MPR121_Channel (mpr121, channel)

Helper class to represent a touch channel on the MPR121. Not meant to be used directly.

raw_value

The raw touch measurement.

release_threshold

The release threshold.

threshold

The touch threshold.

value

Whether the touch pad is being touched or not.

CHAPTER 7

Indices and tables

- genindex
- modindex
- search

Python Module Index

a

adafruit_mpr121, 15

Index

A

adafruit_mpr121 (*module*), 15

B

baseline_data() (*adafruit_mpr121.MPR121 method*), 15

F

filtered_data() (*adafruit_mpr121.MPR121 method*), 15

I

is_touched() (*adafruit_mpr121.MPR121 method*), 15

M

MPR121 (*class in adafruit_mpr121*), 15

MPR121_Channel (*class in adafruit_mpr121*), 16

R

raw_value (*adafruit_mpr121.MPR121_Channel attribute*), 16

release_threshold (*adafruit_mpr121.MPR121_Channel attribute*), 16

reset() (*adafruit_mpr121.MPR121 method*), 15

T

threshold (*adafruit_mpr121.MPR121_Channel attribute*), 16

touched() (*adafruit_mpr121.MPR121 method*), 16

touched_pins (*adafruit_mpr121.MPR121 attribute*), 16

V

value (*adafruit_mpr121.MPR121_Channel attribute*), 16