
AdafruitMPRLS Library Documentation

Release 1.0

ladyada

Mar 02, 2021

Contents

1	Dependencies	3
2	Installing from PyPI	5
3	Usage Example	7
4	Contributing	9
5	Documentation	11
6	Table of Contents	13
6.1	Simple test	13
6.2	adafruit_mprls	14
6.2.1	Implementation Notes	14
7	Indices and tables	15
Python Module Index		17
Index		19

CircuitPython library to support Honeywell MPRLS digital pressure sensors.

CHAPTER 1

Dependencies

This driver depends on:

- Adafruit CircuitPython
- Bus Device

Please ensure all dependencies are available on the CircuitPython filesystem. This is easily achieved by downloading the [Adafruit library and driver bundle](#).

CHAPTER 2

Installing from PyPI

On supported GNU/Linux systems like the Raspberry Pi, you can install the driver locally [from PyPI](#). To install for current user:

```
pip3 install adafruit-circuitpython-mprls
```

To install system-wide (this may be required in some cases):

```
sudo pip3 install adafruit-circuitpython-mprls
```

To install in a virtual environment in your current project:

```
mkdir project-name && cd project-name  
python3 -m venv .env  
source .env/bin/activate  
pip3 install adafruit-circuitpython-mprls
```


CHAPTER 3

Usage Example

```
import time
import board
import busio
import adafruit_mprls

i2c = busio.I2C(board.SCL, board.SDA)

# Simplest use, connect to default over I2C
mpr = adafruit_mprls.MPRLS(i2c, psi_min=0, psi_max=25)

while True:
    print((mpr.pressure,))
    time.sleep(1)
```


CHAPTER 4

Contributing

Contributions are welcome! Please read our [Code of Conduct](#) before contributing to help this project stay welcoming.

CHAPTER 5

Documentation

For information on building library documentation, please check out [this guide](#).

CHAPTER 6

Table of Contents

6.1 Simple test

Ensure your device works with this simple test.

Listing 1: examples/mprls_simpletest.py

```
1 # SPDX-FileCopyrightText: 2021 ladyada for Adafruit Industries
2 # SPDX-License-Identifier: MIT
3
4 import time
5 import board
6 import busio
7 import adafruit_mprls
8
9 i2c = busio.I2C(board.SCL, board.SDA)
10
11 # Simplest use, connect to default over I2C
12 mpr = adafruit_mprls.MPRLS(i2c, psi_min=0, psi_max=25)
13
14 # You can also specify both reset and eoc pins
15 """
16 import digitalio
17 reset = digitalio.DigitalInOut(board.D5)
18 eoc = digitalio.DigitalInOut(board.D6)
19 mpr = adafruit_mprls.MPRLS(i2c, eoc_pin=eoc, reset_pin=reset,
20                           psi_min=0, psi_max=25)
21 """
22
23 while True:
24     print((mpr.pressure,))
25     time.sleep(1)
```

6.2 adafruit_mprls

CircuitPython library to support Honeywell MPRLS digital pressure sensors

- Author(s): ladyada

6.2.1 Implementation Notes

Hardware:

Software and Dependencies:

- Adafruit CircuitPython firmware for the supported boards: <https://github.com/adafruit/circuitpython/releases>
- Adafruit's Bus Device library: https://github.com/adafruit/Adafruit_CircuitPython_BusDevice

```
class adafruit_mprls.MPRLS(i2c_bus, *, addr=24, reset_pin=None, eoc_pin=None, psi_min=0,
                            psi_max=25)
```

Driver base for the MPRLS pressure sensor
:param i2c_bus: The `busio.I2C` object to use. This is the only required parameter.
:param int addr: The optional I2C address, defaults to 0x18
:param microcontroller.Pin reset_pin: Optional digitalio pin for hardware resetting
:param microcontroller.Pin eoc_pin: Optional digitalio pin for getting End Of Conversion signal
:param float psi_min: The minimum pressure in PSI, defaults to 0
:param float psi_max: The maximum pressure in PSI, defaults to 25

pressure

The measured pressure, in hPa

CHAPTER 7

Indices and tables

- genindex
- modindex
- search

Python Module Index

a

adafruit_mprls, 13

Index

A

`adafruit_mprls` (*module*), 13

M

`MPRLS` (*class in adafruit_mprls*), 14

P

`pressure` (*adafruit_mprls.MPRLS attribute*), 14