

---

# AdafruitPN532 Library Documentation

*Release 1.0*

**ladyada**

**Jul 09, 2020**



---

## Contents

---

<b>1</b>	<b>Dependencies</b>	<b>3</b>
1.1	Installing from PyPI . . . . .	3
<b>2</b>	<b>Usage Example</b>	<b>5</b>
<b>3</b>	<b>Contributing</b>	<b>7</b>
<b>4</b>	<b>Documentation</b>	<b>9</b>
<b>5</b>	<b>Table of Contents</b>	<b>11</b>
5.1	Simple test . . . . .	11
5.2	adafruit_pn532 . . . . .	12
5.2.1	Implementation Notes . . . . .	12
5.3	adafruit_pn532.i2c . . . . .	13
5.4	adafruit_pn532.spi . . . . .	13
5.5	adafruit_pn532.uart . . . . .	14
<b>6</b>	<b>Indices and tables</b>	<b>15</b>
	<b>Python Module Index</b>	<b>17</b>
	<b>Index</b>	<b>19</b>



CircuitPython driver for the [PN532 NFC/RFID Breakout](#) and [PN532 NFC/RFID Shield](#)



# CHAPTER 1

---

## Dependencies

---

This driver depends on:

- [Adafruit CircuitPython](#)
- [Bus Device](#)

Please ensure all dependencies are available on the CircuitPython filesystem. This is easily achieved by downloading the [Adafruit library and driver bundle](#).

### 1.1 Installing from PyPI

On supported GNU/Linux systems like the Raspberry Pi, you can install the driver locally [from PyPI](#). To install for current user:

```
pip3 install adafruit-circuitpython-pn532
```

To install system-wide (this may be required in some cases):

```
sudo pip3 install adafruit-circuitpython-pn532
```

To install in a virtual environment in your current project:

```
mkdir project-name && cd project-name
python3 -m venv .env
source .env/bin/activate
pip3 install adafruit-circuitpython-pn532
```





## CHAPTER 2

---

### Usage Example

---

Check `examples/pn532_simpletest.py` for usage example



## CHAPTER 3

---

### Contributing

---

Contributions are welcome! Please read our [Code of Conduct](#) before contributing to help this project stay welcoming.



## CHAPTER 4

---

### Documentation

---

For information on building library documentation, please check out [this guide](#).



## 5.1 Simple test

Ensure your device works with this simple test.

Listing 1: examples/pn532\_simpletest.py

```
1  """
2  This example shows connecting to the PN532 with I2C (requires clock
3  stretching support), SPI, or UART. SPI is best, it uses the most pins but
4  is the most reliable and universally supported.
5  After initialization, try waving various 13.56MHz RFID cards over it!
6  """
7
8  import board
9  import busio
10 from digitalio import DigitalInOut
11
12 #
13 # NOTE: pick the import that matches the interface being used
14 #
15 from adafruit_pn532.i2c import PN532_I2C
16
17 # from adafruit_pn532.spi import PN532_SPI
18 # from adafruit_pn532.uart import PN532_UART
19
20 # I2C connection:
21 i2c = busio.I2C(board.SCL, board.SDA)
22
23 # Non-hardware
24 # pn532 = PN532_I2C(i2c, debug=False)
25
26 # With I2C, we recommend connecting RSTPD_N (reset) to a digital pin for manual
27 # hardware reset
```

(continues on next page)

(continued from previous page)

```

28 reset_pin = DigitalInOut(board.D6)
29 # On Raspberry Pi, you must also connect a pin to P32 "H_Request" for hardware
30 # wakeup! this means we don't need to do the I2C clock-stretch thing
31 req_pin = DigitalInOut(board.D12)
32 pn532 = PN532_I2C(i2c, debug=False, reset=reset_pin, req=req_pin)
33
34 # SPI connection:
35 # spi = busio.SPI(board.SCK, board.MOSI, board.MISO)
36 # cs_pin = DigitalInOut(board.D5)
37 # pn532 = PN532_SPI(spi, cs_pin, debug=False)
38
39 # UART connection
40 # uart = busio.UART(board.TX, board.RX, baudrate=115200, timeout=100)
41 # pn532 = PN532_UART(uart, debug=False)
42
43 ic, ver, rev, support = pn532.firmware_version
44 print("Found PN532 with firmware version: {0}.{1}".format(ver, rev))
45
46 # Configure PN532 to communicate with MiFare cards
47 pn532.SAM_configuration()
48
49 print("Waiting for RFID/NFC card...")
50 while True:
51     # Check if a card is available to read
52     uid = pn532.read_passive_target(timeout=0.5)
53     print(".", end="")
54     # Try again if no card is available.
55     if uid is None:
56         continue
57     print("Found card with UID:", [hex(i) for i in uid])

```

## 5.2 adafruit\_pn532

This module will let you communicate with a PN532 RFID/NFC shield or breakout using I2C, SPI or UART.

- Author(s): Original Raspberry Pi code by Tony DiCola, CircuitPython by ladyada

### 5.2.1 Implementation Notes

#### Hardware:

- Adafruit PN532 Breakout
- Adafruit PN532 Shield

#### Software and Dependencies:

- Adafruit CircuitPython firmware for the supported boards: <https://github.com/adafruit/circuitpython/releases>
- Adafruit's Bus Device library: [https://github.com/adafruit/Adafruit\\_CircuitPython\\_BusDevice](https://github.com/adafruit/Adafruit_CircuitPython_BusDevice)

**exception** `adafruit_pn532.adafruit_pn532.BusyError`  
Base class for exceptions in this module.

**class** `adafruit_pn532.adafruit_pn532.PN532` (\*, *debug=False*, *reset=None*)  
PN532 driver base, must be extended for I2C/SPI/UART interfacing



**SAM\_configuration()**

Configure the PN532 to read MiFare cards.

**call\_function**(*command, response\_length=0, params=[], timeout=1*)

Send specified command to the PN532 and expect up to *response\_length* bytes back in a response. Note that less than the expected bytes might be returned! Params can optionally specify an array of bytes to send as parameters to the function call. Will wait up to *timeout* seconds for a response and return a bytearray of response bytes, or None if no response is available within the timeout.

**firmware\_version**

Call PN532 GetFirmwareVersion function and return a tuple with the IC, Ver, Rev, and Support values.

**mifare\_classic\_authenticate\_block**(*uid, block\_number, key\_number, key*)

Authenticate specified block number for a MiFare classic card. Uid should be a byte array with the UID of the card, block number should be the block to authenticate, key number should be the key type (like MIFARE\_CMD\_AUTH\_A or MIFARE\_CMD\_AUTH\_B), and key should be a byte array with the key data. Returns True if the block was authenticated, or False if not authenticated.

**mifare\_classic\_read\_block**(*block\_number*)

Read a block of data from the card. Block number should be the block to read. If the block is successfully read a bytearray of length 16 with data starting at the specified block will be returned. If the block is not read then None will be returned.

**mifare\_classic\_write\_block**(*block\_number, data*)

Write a block of data to the card. Block number should be the block to write and data should be a byte array of length 16 with the data to write. If the data is successfully written then True is returned, otherwise False is returned.

**ntag2xx\_read\_block**(*block\_number*)

Read a block of data from the card. Block number should be the block to read. If the block is successfully read a bytearray of length 16 with data starting at the specified block will be returned. If the block is not read then None will be returned.

**ntag2xx\_write\_block**(*block\_number, data*)

Write a block of data to the card. Block number should be the block to write and data should be a byte array of length 4 with the data to write. If the data is successfully written then True is returned, otherwise False is returned.

**read\_passive\_target**(*card\_baud=<sphinx.ext.autodoc.importer.\_MockObject object>, timeout=1*)

Wait for a MiFare card to be available and return its UID when found. Will wait up to *timeout* seconds and return None if no card is found, otherwise a bytearray with the UID of the found card is returned.

## 5.3 adafruit\_pn532.i2c

This module will let you communicate with a PN532 RFID/NFC shield or breakout using I2C.

- **Author(s):** Original Raspberry Pi code by Tony DiCola, CircuitPython by ladyada, refactor by Carter Nelson

**class** `adafruit_pn532.i2c.PN532_I2C`(*i2c, \*, irq=None, reset=None, req=None, debug=False*)

Driver for the PN532 connected over I2C.

## 5.4 adafruit\_pn532.spi

This module will let you communicate with a PN532 RFID/NFC shield or breakout using SPI.

- **Author(s):** Original Raspberry Pi code by Tony DiCola, CircuitPython by ladyada, refactor by Carter Nelson

**class** adafruit\_pn532.spi.**PN532\_SPI** (*spi, cs\_pin, \*, irq=None, reset=None, debug=False*)

Driver for the PN532 connected over SPI. Pass in a hardware or bitbang SPI device & chip select digitalInOut pin. Optional IRQ pin (not used), reset pin and debugging output.

adafruit\_pn532.spi.**reverse\_bit** (*num*)

Turn an LSB byte to an MSB byte, and vice versa. Used for SPI as it is LSB for the PN532, but 99% of SPI implementations are MSB only!

## 5.5 adafruit\_pn532.uart

This module will let you communicate with a PN532 RFID/NFC shield or breakout using UART.

- **Author(s):** Original Raspberry Pi code by Tony DiCola, CircuitPython by ladyada, refactor by Carter Nelson

**class** adafruit\_pn532.uart.**PN532\_UART** (*uart, \*, irq=None, reset=None, debug=False*)

Driver for the PN532 connected over Serial UART

## CHAPTER 6

---

### Indices and tables

---

- `genindex`
- `modindex`
- `search`



### a

`adafruit_pn532.adafruit_pn532`, [12](#)  
`adafruit_pn532.i2c`, [13](#)  
`adafruit_pn532.spi`, [13](#)  
`adafruit_pn532.uart`, [14](#)



## A

`adafruit_pn532.adafruit_pn532` (module), 12  
`adafruit_pn532.i2c` (module), 13  
`adafruit_pn532.spi` (module), 13  
`adafruit_pn532.uart` (module), 14

## B

`BusyError`, 12

## C

`call_function()` (`adafruit_pn532.adafruit_pn532.PN532`  
method), 13

## F

`firmware_version` (`adafruit_pn532.adafruit_pn532.PN532`  
attribute), 13

## M

`mifare_classic_authenticate_block()`  
(`adafruit_pn532.adafruit_pn532.PN532`  
method), 13

`mifare_classic_read_block()`  
(`adafruit_pn532.adafruit_pn532.PN532`  
method), 13

`mifare_classic_write_block()`  
(`adafruit_pn532.adafruit_pn532.PN532`  
method), 13

## N

`ntag2xx_read_block()`  
(`adafruit_pn532.adafruit_pn532.PN532`  
method), 13

`ntag2xx_write_block()`  
(`adafruit_pn532.adafruit_pn532.PN532`  
method), 13

## P

`PN532` (class in `adafruit_pn532.adafruit_pn532`), 12  
`PN532_I2C` (class in `adafruit_pn532.i2c`), 13

`PN532_SPI` (class in `adafruit_pn532.spi`), 14  
`PN532_UART` (class in `adafruit_pn532.uart`), 14

## R

`read_passive_target()`  
(`adafruit_pn532.adafruit_pn532.PN532`  
method), 13

`reverse_bit()` (in module `adafruit_pn532.spi`), 14

## S

`S2M_configuration()`  
(`adafruit_pn532.adafruit_pn532.PN532`  
method), 12