
AdafruitRGB*DisplayLibraryDocumentation*

Release 1.0

Michale McWethy

Oct 10, 2019

Contents

1	Dependencies	3
2	Usage Example	5
3	Contributing	7
4	Building locally	9
4.1	Sphinx documentation	9
5	Table of Contents	11
5.1	Simple test	11
5.2	adafruit_rgb_display.rgb	13
5.3	adafruit_rgb_display.hx8353	14
5.4	adafruit_rgb_display.ili9341	14
5.5	adafruit_rgb_display.s6d02a1	15
5.6	adafruit_rgb_display.ssd1331	15
5.7	adafruit_rgb_display.ssd1351	16
5.8	adafruit_rgb_display.st7735	16
6	Indices and tables	17
	Python Module Index	19
	Index	21

Port of display drivers from <https://github.com/adafruit/micropython-adafruit-rgb-display> to Adafruit CircuitPython for use on Adafruit's SAMD21-based and other CircuitPython boards.

Note: This driver currently won't work on micropython.org firmware, instead you want the micropython-adafruit-rgb-display driver linked above!

This CircuitPython driver currently supports displays that use the following display-driver chips: HX8353, HX8357, ILI9341, S6D02A1, ST7789, SSD1331, SSD1351, and ST7735.

CHAPTER 1

Dependencies

This driver depends on:

- [Adafruit CircuitPython](#)
- [Bus Device](#)

Please ensure all dependencies are available on the CircuitPython filesystem. This is easily achieved by downloading the [Adafruit library and driver bundle](#).

CHAPTER 2

Usage Example

```
import busio
import digitalio
from board import SCK, MOSI, MISO, D2, D3

from adafruit_rgb_display import color565
import adafruit_rgb_display.ili9341 as ili9341

# Configuration for CS and DC pins:
CS_PIN = D2
DC_PIN = D3

# Setup SPI bus using hardware SPI:
spi = busio.SPI(clock=SCK, MOSI=MOSI, MISO=MISO)

# Create the ILI9341 display:
display = ili9341.ILI9341(spi, cs=digitalio.DigitalInOut(CS_PIN),
                          dc=digitalio.DigitalInOut(DC_PIN))

# Main loop:
while True:
    # Clear the display
    display.fill(0)
    # Draw a red pixel in the center.
    display.pixel(120, 160, color565(255, 0, 0))
    # Pause 2 seconds.
    time.sleep(2)
    # Clear the screen blue.
    display.fill(color565(0, 0, 255))
    # Pause 2 seconds.
    time.sleep(2)
```


CHAPTER 3

Contributing

Contributions are welcome! Please read our [Code of Conduct](#) before contributing to help this project stay welcoming.

CHAPTER 4

Building locally

To build this library locally you'll need to install the `circuitpython-build-tools` package.

```
python3 -m venv .env
source .env/bin/activate
pip install circuitpython-build-tools
```

Once installed, make sure you are in the virtual environment:

```
source .env/bin/activate
```

Then run the build:

```
circuitpython-build-bundles --filename_prefix adafruit-circuitpython-rgb_display --
↳library_location .
```

4.1 Sphinx documentation

Sphinx is used to build the documentation based on rST files and comments in the code. First, install dependencies (feel free to reuse the virtual environment from above):

```
python3 -m venv .env
source .env/bin/activate
pip install Sphinx sphinx-rtd-theme
```

Now, once you have the virtual environment activated:

```
cd docs
sphinx-build -E -W -b html . _build/html
```

This will output the documentation to `docs/_build/html`. Open the `index.html` in your browser to view them. It will also (due to `-W`) error out on any warning like Travis will. This is a good way to locally verify it will pass.

5.1 Simple test

Ensure your device works with this simple test.

Listing 1: examples/rgb_display_simpletest.py

```
1  # Quick test of TFT FeatherWing (ST7789) with Feather M0 or M4
2  # This will work even on a device running displayio
3  # Will fill the TFT black and put a red pixel in the center, wait 2 seconds,
4  # then fill the screen blue (with no pixel), wait 2 seconds, and repeat.
5  import time
6  import random
7  import digitalio
8  import board
9  import displayio
10
11  from adafruit_rgb_display.rgb import color565
12  import adafruit_rgb_display.st7789 as st7789
13
14  displayio.release_displays()
15
16  # Configuratin for CS and DC pins (these are FeatherWing defaults on M0/M4):
17  cs_pin = digitalio.DigitalInOut(board.D5)
18  dc_pin = digitalio.DigitalInOut(board.D6)
19  reset_pin = digitalio.DigitalInOut(board.D9)
20
21  # Config for display baudrate (default max is 24mhz):
22  BAUDRATE = 24000000
23
24  # Setup SPI bus using hardware SPI:
25  spi = board.SPI()
26
27  # Create the ST7789 display:
```

(continues on next page)

(continued from previous page)

```

28 display = st7789.ST7789(spi, cs=cs_pin, dc=dc_pin, rst=reset_pin, baudrate=BAUDRATE)
29
30 # Main loop:
31 while True:
32     # Fill the screen red, green, blue, then black:
33     for color in ((255, 0, 0), (0, 255, 0), (0, 0, 255)):
34         display.fill(color565(color))
35     # Clear the display
36     display.fill(0)
37     # Draw a red pixel in the center.
38     display.pixel(display.width//2, display.height//2, color565(255, 0, 0))
39     # Pause 2 seconds.
40     time.sleep(2)
41     # Clear the screen a random color
42     display.fill(color565(random.randint(0, 255),
43                             random.randint(0, 255),
44                             random.randint(0, 255)))
45     # Pause 2 seconds.
46     time.sleep(2)

```

Listing 2: examples/rgb_display_ili9341test.py

```

1  # Quick test of TFT FeatherWing (ILI9341) with Feather M0 or M4
2  # Will fill the TFT black and put a red pixel in the center, wait 2 seconds,
3  # then fill the screen blue (with no pixel), wait 2 seconds, and repeat.
4  import time
5  import random
6  import busio
7  import digitalio
8  import board
9
10 from adafruit_rgb_display.rgb import color565
11 import adafruit_rgb_display.ili9341 as ili9341
12
13
14 # Configuratin for CS and DC pins (these are FeatherWing defaults on M0/M4):
15 cs_pin = digitalio.DigitalInOut(board.D9)
16 dc_pin = digitalio.DigitalInOut(board.D10)
17
18 # Config for display baudrate (default max is 24mhz):
19 BAUDRATE = 24000000
20
21 # Setup SPI bus using hardware SPI:
22 spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)
23
24 # Create the ILI9341 display:
25 display = ili9341.ILI9341(spi, cs=cs_pin, dc=dc_pin, baudrate=BAUDRATE)
26
27 # Main loop:
28 while True:
29     # Fill the screen red, green, blue, then black:
30     for color in ((255, 0, 0), (0, 255, 0), (0, 0, 255)):
31         display.fill(color565(color))
32     # Clear the display
33     display.fill(0)
34     # Draw a red pixel in the center.

```

(continues on next page)

(continued from previous page)

```

35 display.pixel(display.width//2, display.height//2, color565(255, 0, 0))
36 # Pause 2 seconds.
37 time.sleep(2)
38 # Clear the screen a random color
39 display.fill(color565(random.randint(0, 255),
40                      random.randint(0, 255),
41                      random.randint(0, 255)))
42 # Pause 2 seconds.
43 time.sleep(2)

```

5.2 adafruit_rgb_display.rgb

Base class for all RGB Display devices

- Author(s): Radomir Dopieralski, Michael McWethy

class adafruit_rgb_display.rgb.**Display**(width, height)

Base class for all RGB display devices :param width: number of pixels wide :param height: number of pixels high

fill(color=0)

Fill the whole display with the specified color.

fill_rectangle(x, y, width, height, color)

Draw a rectangle at specified position with specified width and height, and fill it with the specified color.

hline(x, y, width, color)

Draw a horizontal line.

image(img, rotation=0)

Set buffer to value of Python Imaging Library image. The image should be in 1 bit mode and a size equal to the display size.

init()

Run the initialization commands.

pixel(x, y, color=None)

Read or write a pixel at a given position.

vline(x, y, height, color)

Draw a vertical line.

class adafruit_rgb_display.rgb.**DisplaySPI**(spi, dc, cs, rst=None, width=1, height=1, baudrate=12000000, polarity=0, phase=0, *, x_offset=0, y_offset=0)

Base class for SPI type devices

read(command=None, count=0)

SPI read from device with optional command

reset()

Reset the device

write(command=None, data=None)

SPI write to the device: commands and data

class adafruit_rgb_display.rgb.**DummyPin**

Can be used in place of a DigitalInOut() when you don't want to skip it.

deinit ()
Dummy DigitalInOut deinit

direction
Dummy direction DigitalInOut property

pull
Dummy pull DigitalInOut property

switch_to_input (*args, **kwargs)
Dummy switch_to_input method

switch_to_output (*args, **kwargs)
Dummy switch_to_output method

value
Dummy value DigitalInOut property

`adafruit_rgb_display.rgb.color565 (r, g=0, b=0)`
Convert red, green and blue values (0-255) into a 16-bit 565 encoding. As a convenience this is also available in the parent `adafruit_rgb_display` package namespace.

5.3 `adafruit_rgb_display.hx8353`

A simple driver for the HX8353-based displays.

- Author(s): Radomir Dopieralski, Michael McWethy

class `adafruit_rgb_display.hx8353.HX8353` (*spi, dc, cs, rst=None, width=128, height=128*)
A simple driver for the HX8353-based displays.

```
>>> import busio
>>> import digitalio
>>> import board
>>> from adafruit_rgb_display import color565
>>> import adafruit_rgb_display.hx8353 as hx8353
>>> spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)
>>> display = hx8353.HX8383(spi, cs=digitalio.DigitalInOut(board.GPIO0),
...     dc=digitalio.DigitalInOut(board.GPIO15))
>>> display.fill(0x7521)
>>> display.pixel(64, 64, 0)
```

5.4 `adafruit_rgb_display.ili9341`

A simple driver for the ILI9341/ILI9340-based displays.

- Author(s): Radomir Dopieralski, Michael McWethy

class `adafruit_rgb_display.ili9341.ILI9341` (*spi, dc, cs, rst=None, width=240, height=320, baudrate=16000000, polarity=0, phase=0*)
A simple driver for the ILI9341/ILI9340-based displays.

```
>>> import busio
>>> import digitalio
>>> import board
>>> from adafruit_rgb_display import color565
```

(continues on next page)

(continued from previous page)

```
>>> import adafruit_rgb_display.ili9341 as ili9341
>>> spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)
>>> display = ili9341.ILI9341(spi, cs=digitalio.DigitalInOut(board.GPIO0),
...     dc=digitalio.DigitalInOut(board.GPIO15))
>>> display.fill(color565(0xff, 0x11, 0x22))
>>> display.pixel(120, 160, 0)
```

scroll (*dy=None*)
 Scroll the display by delta y

5.5 adafruit_rgb_display.s6d02a1

A simple driver for the S6D02A1-based displays.

- Author(s): Radomir Dopieralski, Michael McWethy

```
class adafruit_rgb_display.s6d02a1.S6D02A1(spi, dc, cs, rst=None, width=128,
                                           height=160)
```

A simple driver for the S6D02A1-based displays.

```
>>> import busio
>>> import digitalio
>>> import board
>>> from adafruit_rgb_display import color565
>>> import adafruit_rgb_display.s6d02a1 as s6d02a1
>>> spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)
>>> display = s6d02a1.S6D02A1(spi, cs=digitalio.DigitalInOut(board.GPIO0),
...     dc=digitalio.DigitalInOut(board.GPIO15), rst=digitalio.DigitalInOut(board.
↳ GPIO16))
>>> display.fill(0x7521)
>>> display.pixel(64, 64, 0)
```

5.6 adafruit_rgb_display.ssd1331

A simple driver for the SSD1331-based displays.

- Author(s): Radomir Dopieralski, Michael McWethy

```
class adafruit_rgb_display.ssd1331.SSD1331(spi, dc, cs, rst=None, width=96, height=64)
```

A simple driver for the SSD1331-based displays.

```
import busio
import digitalio
import board
from adafruit_rgb_display import color565
import adafruit_rgb_display.ssd1331 as ssd1331
spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)
display = ssd1331.SSD1331(spi, cs=digitalio.DigitalInOut(board.GPIO0),
                          dc=digitalio.DigitalInOut(board.GPIO15),
                          rst=digitalio.DigitalInOut(board.GPIO16))

display.fill(0x7521)
display.pixel(32, 32, 0)
```

```
write (command=None, data=None)
    write procedure specific to SSD1331
```

5.7 adafruit_rgb_display.ssd1351

A simple driver for the SSD1351-based displays.

- Author(s): Radomir Dopieralski, Michael McWethy

```
class adafruit_rgb_display.ssd1351.SSD1351 (spi, dc, cs, rst=None, width=128,
                                             height=128)
```

A simple driver for the SSD1351-based displays.

```
>>> import busio
>>> import digitalio
>>> import board
>>> from adafruit_rgb_display import color565
>>> import adafruit_rgb_display.ssd1351 as ssd1351
>>> spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)
>>> display = ssd1351.SSD1351(spi, cs=digitalio.DigitalInOut(board.GPIO0),
...     dc=digitalio.DigitalInOut(board.GPIO15), rst=digitalio.DigitalInOut(board.
↳ GPIO16))
>>> display.fill(0x7521)
>>> display.pixel(32, 32, 0)
```

5.8 adafruit_rgb_display.st7735

A simple driver for the ST7735-based displays.

- Author(s): Radomir Dopieralski, Michael McWethy

```
class adafruit_rgb_display.st7735.ST7735 (spi, dc, cs, rst=None, width=128, height=128)
```

A simple driver for the ST7735-based displays.

```
>>> import busio
>>> import digitalio
>>> import board
>>> from adafruit_rgb_display import color565
>>> import adafruit_rgb_display.st7735 as st7735
>>> spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)
>>> display = st7735.ST7735(spi, cs=digitalio.DigitalInOut(board.GPIO0),
...     dc=digitalio.DigitalInOut(board.GPIO15), rst=digitalio.DigitalInOut(board.
↳ GPIO16))
>>> display.fill(0x7521)
>>> display.pixel(64, 64, 0)
```

```
class adafruit_rgb_display.st7735.ST7735R (spi, dc, cs, rst=None, width=128, height=160)
```

A simple driver for the ST7735R-based displays.

```
init ()
```

Run the initialization commands.

CHAPTER 6

Indices and tables

- `genindex`
- `modindex`
- `search`

a

`adafruit_rgb_display.hx8353`, [14](#)
`adafruit_rgb_display.ili9341`, [14](#)
`adafruit_rgb_display.rgb`, [13](#)
`adafruit_rgb_display.s6d02a1`, [15](#)
`adafruit_rgb_display.ssd1331`, [15](#)
`adafruit_rgb_display.ssd1351`, [16](#)
`adafruit_rgb_display.st7735`, [16](#)

A

`adafruit_rgb_display.hx8353` (module), 14
`adafruit_rgb_display.ili9341` (module), 14
`adafruit_rgb_display.rgb` (module), 13
`adafruit_rgb_display.s6d02a1` (module), 15
`adafruit_rgb_display.ssd1331` (module), 15
`adafruit_rgb_display.ssd1351` (module), 16
`adafruit_rgb_display.st7735` (module), 16

C

`color565()` (in module `adafruit_rgb_display.rgb`), 14

D

`deinit()` (`adafruit_rgb_display.rgb.DummyPin` method), 13
`direction` (`adafruit_rgb_display.rgb.DummyPin` attribute), 14
`Display` (class in `adafruit_rgb_display.rgb`), 13
`DisplaySPI` (class in `adafruit_rgb_display.rgb`), 13
`DummyPin` (class in `adafruit_rgb_display.rgb`), 13

F

`fill()` (`adafruit_rgb_display.rgb.Display` method), 13
`fill_rectangle()` (`adafruit_rgb_display.rgb.Display` method), 13

H

`hline()` (`adafruit_rgb_display.rgb.Display` method), 13
`HX8353` (class in `adafruit_rgb_display.hx8353`), 14

I

`ILI9341` (class in `adafruit_rgb_display.ili9341`), 14
`image()` (`adafruit_rgb_display.rgb.Display` method), 13
`init()` (`adafruit_rgb_display.rgb.Display` method), 13
`init()` (`adafruit_rgb_display.st7735.ST7735R` method), 16

P

`pixel()` (`adafruit_rgb_display.rgb.Display` method), 13
`pull` (`adafruit_rgb_display.rgb.DummyPin` attribute), 14

R

`read()` (`adafruit_rgb_display.rgb.DisplaySPI` method), 13
`reset()` (`adafruit_rgb_display.rgb.DisplaySPI` method), 13

S

`S6D02A1` (class in `adafruit_rgb_display.s6d02a1`), 15
`scroll()` (`adafruit_rgb_display.ili9341.ILI9341` method), 15
`SSD1331` (class in `adafruit_rgb_display.ssd1331`), 15
`SSD1351` (class in `adafruit_rgb_display.ssd1351`), 16
`ST7735` (class in `adafruit_rgb_display.st7735`), 16
`ST7735R` (class in `adafruit_rgb_display.st7735`), 16
`switch_to_input()` (`adafruit_rgb_display.rgb.DummyPin` method), 14
`switch_to_output()` (`adafruit_rgb_display.rgb.DummyPin` method), 14

V

`value` (`adafruit_rgb_display.rgb.DummyPin` attribute), 14
`vline()` (`adafruit_rgb_display.rgb.Display` method), 13

W

`write()` (`adafruit_rgb_display.rgb.DisplaySPI` method), 13
`write()` (`adafruit_rgb_display.ssd1331.SSD1331` method), 15