
AdafruitRGB*Display Library Documentation*

Release 1.0

Michale McWethy

Oct 11, 2019

Contents

1	Dependencies	3
2	Usage Example	5
3	Contributing	7
4	Building locally	9
4.1	Sphinx documentation	9
5	Table of Contents	11
5.1	Simple test	11
5.2	adafruit_rgb_display.rgb	13
5.3	adafruit_rgb_display.hx8353	14
5.4	adafruit_rgb_display.il19341	14
5.5	adafruit_rgb_display.s6d02a1	15
5.6	adafruit_rgb_display.ssd1331	15
5.7	adafruit_rgb_display.ssd1351	16
5.8	adafruit_rgb_display.st7735	16
6	Indices and tables	19
Python Module Index		21
Index		23

Port of display drivers from <https://github.com/adafruit/micropython-adafruit-rgb-display> to Adafruit CircuitPython for use on Adafruit's SAMD21-based and other CircuitPython boards.

Note: This driver currently won't work on micropython.org firmware, instead you want the micropython-adafruit-rgb-display driver linked above!

This CircuitPython driver currently supports displays that use the following display-driver chips: HX8353, HX8357, ILI9341, S6D02A1, ST7789, SSD1331, SSD1351, and ST7735.

CHAPTER 1

Dependencies

This driver depends on:

- Adafruit CircuitPython
- Bus Device

Please ensure all dependencies are available on the CircuitPython filesystem. This is easily achieved by downloading the [Adafruit library and driver bundle](#).

CHAPTER 2

Usage Example

```
import busio
import digitalio
from board import SCK, MOSI, MISO, D2, D3

from adafruit_rgb_display import color565
import adafruit_rgb_display.ilis341 as ilis341

# Configuration for CS and DC pins:
CS_PIN = D2
DC_PIN = D3

# Setup SPI bus using hardware SPI:
spi = busio.SPI(clock=SCK, MOSI=MOSI, MISO=MISO)

# Create the ILI9341 display:
display = ilis341.ILI9341(spi, cs=digitalio.DigitalInOut(CS_PIN),
                           dc=digitalio.DigitalInOut(DC_PIN))

# Main loop:
while True:
    # Clear the display
    display.fill(0)
    # Draw a red pixel in the center.
    display.pixel(120, 160, color565(255, 0, 0))
    # Pause 2 seconds.
    time.sleep(2)
    # Clear the screen blue.
    display.fill(color565(0, 0, 255))
    # Pause 2 seconds.
    time.sleep(2)
```


CHAPTER 3

Contributing

Contributions are welcome! Please read our [Code of Conduct](#) before contributing to help this project stay welcoming.

CHAPTER 4

Building locally

To build this library locally you'll need to install the `circuitpython-build-tools` package.

```
python3 -m venv .env
source .env/bin/activate
pip install circuitpython-build-tools
```

Once installed, make sure you are in the virtual environment:

```
source .env/bin/activate
```

Then run the build:

```
circuitpython-build-bundles --filename_prefix adafruit-circuitpython-rgb_display --
˓→library_location .
```

4.1 Sphinx documentation

Sphinx is used to build the documentation based on rST files and comments in the code. First, install dependencies (feel free to reuse the virtual environment from above):

```
python3 -m venv .env
source .env/bin/activate
pip install Sphinx sphinx-rtd-theme
```

Now, once you have the virtual environment activated:

```
cd docs
sphinx-build -E -W -b html . _build/html
```

This will output the documentation to `docs/_build/html`. Open the `index.html` in your browser to view them. It will also (due to `-W`) error out on any warning like Travis will. This is a good way to locally verify it will pass.

CHAPTER 5

Table of Contents

5.1 Simple test

Ensure your device works with this simple test.

Listing 1: examples/rgb_display_simpletest.py

```
1 # Quick test of TFT FeatherWing (ST7789) with Feather M0 or M4
2 # This will work even on a device running displayio
3 # Will fill the TFT black and put a red pixel in the center, wait 2 seconds,
4 # then fill the screen blue (with no pixel), wait 2 seconds, and repeat.
5 import time
6 import random
7 import digitalio
8 import board
9 import displayio
10
11 from adafruit_rgb_display.rgb import color565
12 import adafruit_rgb_display.st7789 as st7789
13
14 displayio.release_displays()
15
16 # Configuratoion for CS and DC pins (these are FeatherWing defaults on M0/M4):
17 cs_pin = digitalio.DigitalInOut(board.D5)
18 dc_pin = digitalio.DigitalInOut(board.D6)
19 reset_pin = digitalio.DigitalInOut(board.D9)
20
21 # Config for display baudrate (default max is 24mhz):
22 BAUDRATE = 24000000
23
24 # Setup SPI bus using hardware SPI:
25 spi = board.SPI()
26
27 # Create the ST7789 display:
```

(continues on next page)

(continued from previous page)

```

28 display = st7789.ST7789(spi, cs=cs_pin, dc=dc_pin, rst=reset_pin, baudrate=BAUDRATE)
29
30 # Main loop:
31 while True:
32     # Fill the screen red, green, blue, then black:
33     for color in ((255, 0, 0), (0, 255, 0), (0, 0, 255)):
34         display.fill(color565(color))
35     # Clear the display
36     display.fill(0)
37     # Draw a red pixel in the center.
38     display.pixel(display.width//2, display.height//2, color565(255, 0, 0))
39     # Pause 2 seconds.
40     time.sleep(2)
41     # Clear the screen a random color
42     display.fill(color565(random.randint(0, 255),
43                           random.randint(0, 255),
44                           random.randint(0, 255)))
45     # Pause 2 seconds.
46     time.sleep(2)

```

Listing 2: examples/rgb_display_ilis341test.py

```

1 # Quick test of TFT FeatherWing (ILI9341) with Feather M0 or M4
2 # Will fill the TFT black and put a red pixel in the center, wait 2 seconds,
3 # then fill the screen blue (with no pixel), wait 2 seconds, and repeat.
4 import time
5 import random
6 import busio
7 import digitalio
8 import board
9
10 from adafruit_rgb_display.rgb import color565
11 import adafruit_rgb_display.ilis341 as ilis341
12
13
14 # Configuration for CS and DC pins (these are FeatherWing defaults on M0/M4):
15 cs_pin = digitalio.DigitalInOut(board.D9)
16 dc_pin = digitalio.DigitalInOut(board.D10)
17
18 # Config for display baudrate (default max is 24mhz):
19 BAUDRATE = 24000000
20
21 # Setup SPI bus using hardware SPI:
22 spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)
23
24 # Create the ILI9341 display:
25 display = ilis341.ILI9341(spi, cs=cs_pin, dc=dc_pin, baudrate=BAUDRATE)
26
27 # Main loop:
28 while True:
29     # Fill the screen red, green, blue, then black:
30     for color in ((255, 0, 0), (0, 255, 0), (0, 0, 255)):
31         display.fill(color565(color))
32     # Clear the display
33     display.fill(0)
34     # Draw a red pixel in the center.

```

(continues on next page)

(continued from previous page)

```

35     display.pixel(display.width//2, display.height//2, color565(255, 0, 0))
36     # Pause 2 seconds.
37     time.sleep(2)
38     # Clear the screen a random color
39     display.fill(color565(random.randint(0, 255),
40                           random.randint(0, 255),
41                           random.randint(0, 255)))
42     # Pause 2 seconds.
43     time.sleep(2)

```

5.2 adafruit_rgb_display.rgb

Base class for all RGB Display devices

- Author(s): Radomir Dopieralski, Michael McWethy

class adafruit_rgb_display.rgb.**Display**(width, height, rotation)

Base class for all RGB display devices :param width: number of pixels wide :param height: number of pixels high

fill(color=0)

Fill the whole display with the specified color.

fill_rectangle(x, y, width, height, color)

Draw a rectangle at specified position with specified width and height, and fill it with the specified color.

hline(x, y, width, color)

Draw a horizontal line.

image(img, rotation=None)

Set buffer to value of Python Imaging Library image. The image should be in 1 bit mode and a size equal to the display size.

init()

Run the initialization commands.

pixel(x, y, color=None)

Read or write a pixel at a given position.

rotation

Set the default rotation

vline(x, y, height, color)

Draw a vertical line.

class adafruit_rgb_display.rgb.**DisplaySPI**(spi, dc, cs, rst=None, width=1, height=1, baudrate=12000000, polarity=0, phase=0, *, x_offset=0, y_offset=0, rotation=0)

Base class for SPI type devices

read(command=None, count=0)

SPI read from device with optional command

reset()

Reset the device

write(command=None, data=None)

SPI write to the device: commands and data

```
class adafruit_rgb_display.rgb.DummyPin
    Can be used in place of a DigitalInOut() when you don't want to skip it.
```

```
    deinit()
        Dummy DigitalInOut deinit
```

```
    direction
        Dummy direction DigitalInOut property
```

```
    pull
        Dummy pull DigitalInOut property
```

```
    switch_to_input(*args, **kwargs)
        Dummy switch_to_input method
```

```
    switch_to_output(*args, **kwargs)
        Dummy switch_to_output method
```

```
    value
        Dummy value DigitalInOut property
```

```
adafruit_rgb_display.rgb.color565(r, g=0, b=0)
```

```
    Convert red, green and blue values (0-255) into a 16-bit 565 encoding. As a convenience this is also available in the parent adafruit_rgb_display package namespace.
```

5.3 adafruit_rgb_display.hx8353

A simple driver for the HX8353-based displays.

- Author(s): Radomir Dopieralski, Michael McWethy

```
class adafruit_rgb_display.hx8353.HX8353(spi, dc, cs, rst=None, width=128, height=128, rotation=0)
```

```
    A simple driver for the HX8353-based displays.
```

```
>>> import busio
>>> import digitalio
>>> import board
>>> from adafruit_rgb_display import color565
>>> import adafruit_rgb_display.hx8353 as hx8353
>>> spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)
>>> display = hx8353.HX8353(spi, cs=digitalio.DigitalInOut(board.GPIO0),
...     dc=digitalio.DigitalInOut(board.GPIO15))
>>> display.fill(0x7521)
>>> display.pixel(64, 64, 0)
```

5.4 adafruit_rgb_display.ilim9341

A simple driver for the ILI9341/ILI9340-based displays.

- Author(s): Radomir Dopieralski, Michael McWethy

```
class adafruit_rgb_display.ilim9341.ILIM9341(spi, dc, cs, rst=None, width=240, height=320,
                                             baudrate=16000000, polarity=0, phase=0, rotation=0)
```

```
    A simple driver for the ILI9341/ILI9340-based displays.
```

```
>>> import busio
>>> import digitalio
>>> import board
>>> from adafruit_rgb_display import color565
>>> import adafruit_rgb_display.ili9341 as ili9341
>>> spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)
>>> display = ili9341.ILI9341(spi, cs=digitalio.DigitalInOut(board.GPIO0),
...     dc=digitalio.DigitalInOut(board.GPIO15))
>>> display.fill(color565(0xff, 0x11, 0x22))
>>> display.pixel(120, 160, 0)
```

scroll (dy=None)
Scroll the display by delta y

5.5 adafruit_rgb_display.s6d02a1

A simple driver for the S6D02A1-based displays.

- Author(s): Radomir Dopieralski, Michael McWethy

```
class adafruit_rgb_display.s6d02a1.S6D02A1(spi, dc, cs, rst=None, width=128, height=160,
                                             rotation=0)
```

A simple driver for the S6D02A1-based displays.

```
>>> import busio
>>> import digitalio
>>> import board
>>> from adafruit_rgb_display import color565
>>> import adafruit_rgb_display.s6d02a1 as s6d02a1
>>> spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)
>>> display = s6d02a1.S6D02A1(spi, cs=digitalio.DigitalInOut(board.GPIO0),
...     dc=digitalio.DigitalInOut(board.GPIO15), rst=digitalio.DigitalInOut(board.
...     GPIO16))
>>> display.fill(0x7521)
>>> display.pixel(64, 64, 0)
```

5.6 adafruit_rgb_display.ssd1331

A simple driver for the SSD1331-based displays.

- Author(s): Radomir Dopieralski, Michael McWethy

```
class adafruit_rgb_display(ssd1331.SSD1331(spi, dc, cs, rst=None, width=96, height=64,
                                              rotation=0))
```

A simple driver for the SSD1331-based displays.

```
import busio
import digitalio
import board
from adafruit_rgb_display import color565
import adafruit_rgb_display.ssd1331 as ssd1331
spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)
display = ssd1331.SSD1331(spi, cs=digitalio.DigitalInOut(board.GPIO0),
                           dc=digitalio.DigitalInOut(board.GPIO15),
```

(continues on next page)

(continued from previous page)

```
rst=digitalio.DigitalInOut(board.GPIO16))

display.fill(0x7521)
display.pixel(32, 32, 0)
```

write (*command=None*, *data=None*)
write procedure specific to SSD1331

5.7 adafruit_rgb_display.ssd1351

A simple driver for the SSD1351-based displays.

- Author(s): Radomir Dopieralski, Michael McWethy

```
class adafruit_rgb_display.ssd1351.SSD1351(spi, dc, cs, rst=None, width=128, height=128,
                                              rotation=0)
```

A simple driver for the SSD1351-based displays.

```
>>> import busio
>>> import digitalio
>>> import board
>>> from adafruit_rgb_display import color565
>>> import adafruit_rgb_display.ssd1351 as ssd1351
>>> spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)
>>> display = ssd1351.SSD1351(spi, cs=digitalio.DigitalInOut(board.GPIO0),
...     dc=digitalio.DigitalInOut(board.GPIO15), rst=digitalio.DigitalInOut(board.
...     ↴GPIO16))
>>> display.fill(0x7521)
>>> display.pixel(32, 32, 0)
```

5.8 adafruit_rgb_display.st7735

A simple driver for the ST7735-based displays.

- Author(s): Radomir Dopieralski, Michael McWethy

```
class adafruit_rgb_display.st7735.ST7735(spi, dc, cs, rst=None, width=128, height=128,
                                             baudrate=16000000, polarity=0, phase=0, *,
                                             x_offset=0, y_offset=0, rotation=0)
```

A simple driver for the ST7735-based displays.

```
>>> import busio
>>> import digitalio
>>> import board
>>> from adafruit_rgb_display import color565
>>> import adafruit_rgb_display.st7735 as st7735
>>> spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)
>>> display = st7735.ST7735(spi, cs=digitalio.DigitalInOut(board.GPIO0),
...     dc=digitalio.DigitalInOut(board.GPIO15), rst=digitalio.DigitalInOut(board.
...     ↴GPIO16))
>>> display.fill(0x7521)
>>> display.pixel(64, 64, 0)
```

```
class adafruit_rgb_display.st7735.ST7735R(spi, dc, cs, rst=None, width=128, height=160,  
baudrate=16000000, polarity=0, phase=0, *,  
x_offset=0, y_offset=0, rotation=0, bgr=False)
```

A simple driver for the ST7735R-based displays.

```
init()
```

Run the initialization commands.

CHAPTER 6

Indices and tables

- genindex
- modindex
- search

Python Module Index

a

adafruit_rgb_display.hx8353, [14](#)
adafruit_rgb_display.ilι9341, [14](#)
adafruit_rgb_display.rgb, [13](#)
adafruit_rgb_display.s6d02a1, [15](#)
adafruit_rgb_display.ssd1331, [15](#)
adafruit_rgb_display.ssd1351, [16](#)
adafruit_rgb_display.st7735, [16](#)

Index

A

adafruit_rgb_display.hx8353 (*module*), 14
adafruit_rgb_display.il19341 (*module*), 14
adafruit_rgb_display.rgb (*module*), 13
adafruit_rgb_display.s6d02a1 (*module*), 15
adafruit_rgb_display.ssd1331 (*module*), 15
adafruit_rgb_display.ssd1351 (*module*), 16
adafruit_rgb_display.st7735 (*module*), 16

C

color565 () (*in module adafruit_rgb_display.rgb*), 14

D

deinit () (*adafruit_rgb_display.rgb.DummyPin method*), 14
direction (*adafruit_rgb_display.rgb.DummyPin attribute*), 14
Display (*class in adafruit_rgb_display.rgb*), 13
DisplaySPI (*class in adafruit_rgb_display.rgb*), 13
DummyPin (*class in adafruit_rgb_display.rgb*), 13

F

fill () (*adafruit_rgb_display.rgb.Display method*), 13
fill_rectangle () (*adafruit_rgb_display.rgb.Display method*), 13

H

hline () (*adafruit_rgb_display.rgb.Display method*), 13

HX8353 (*class in adafruit_rgb_display.hx8353*), 14

I

IL19341 (*class in adafruit_rgb_display.il19341*), 14
image () (*adafruit_rgb_display.rgb.Display method*), 13
init () (*adafruit_rgb_display.rgb.Display method*), 13
init () (*adafruit_rgb_display.st7735.ST7735R method*), 17

P

pixel () (*adafruit_rgb_display.rgb.Display method*), 13
pull (*adafruit_rgb_display.rgb.DummyPin attribute*), 14

R

read () (*adafruit_rgb_display.rgb.DisplaySPI method*), 13
reset () (*adafruit_rgb_display.rgb.DisplaySPI method*), 13
rotation (*adafruit_rgb_display.rgb.Display attribute*), 13

S

S6D02A1 (*class in adafruit_rgb_display.s6d02a1*), 15
scroll () (*adafruit_rgb_display.il19341.IL19341 method*), 15
SSD1331 (*class in adafruit_rgb_display.ssd1331*), 15
SSD1351 (*class in adafruit_rgb_display.ssd1351*), 16
ST7735 (*class in adafruit_rgb_display.st7735*), 16
ST7735R (*class in adafruit_rgb_display.st7735*), 16
switch_to_input () (*adafruit_rgb_display.rgb.DummyPin method*), 14
switch_to_output () (*adafruit_rgb_display.rgb.DummyPin method*), 14

V

value (*adafruit_rgb_display.rgb.DummyPin attribute*), 14
vline () (*adafruit_rgb_display.rgb.Display method*), 13

W

write () (*adafruit_rgb_display.rgb.DisplaySPI method*), 13
write () (*adafruit_rgb_display.ssd1331.SSD1331 method*), 16