

---

# **AdafruitRGB***Display Library Documentation*

***Release 1.0***

**Michale McWethy**

**Oct 23, 2019**



---

## Contents

---

<b>1</b>	<b>Dependencies</b>	<b>3</b>
<b>2</b>	<b>Installing from PyPI</b>	<b>5</b>
<b>3</b>	<b>Usage Example</b>	<b>7</b>
<b>4</b>	<b>Contributing</b>	<b>9</b>
<b>5</b>	<b>Documentation</b>	<b>11</b>
<b>6</b>	<b>Table of Contents</b>	<b>13</b>
6.1	Simple test .....	13
6.2	adafruit_rgb_display.rgb .....	15
6.3	adafruit_rgb_display.hx8353 .....	16
6.4	adafruit_rgb_display.il19341 .....	16
6.5	adafruit_rgb_display.s6d02a1 .....	17
6.6	adafruit_rgb_display.ssd1331 .....	17
6.7	adafruit_rgb_display.ssd1351 .....	18
6.8	adafruit_rgb_display.st7735 .....	18
<b>7</b>	<b>Indices and tables</b>	<b>21</b>
<b>Python Module Index</b>		<b>23</b>
<b>Index</b>		<b>25</b>



Port of display drivers from <https://github.com/adafruit/micropython-adafruit-rgb-display> to Adafruit CircuitPython for use on Adafruit's SAMD21-based and other CircuitPython boards.

---

**Note:** This driver currently won't work on micropython.org firmware, instead you want the micropython-adafruit-rgb-display driver linked above!

---

This CircuitPython driver currently supports displays that use the following display-driver chips: HX8353, HX8357, ILI9341, S6D02A1, ST7789, SSD1331, SSD1351, and ST7735.



# CHAPTER 1

---

## Dependencies

---

This driver depends on:

- Adafruit CircuitPython
- Bus Device

Please ensure all dependencies are available on the CircuitPython filesystem. This is easily achieved by downloading the [Adafruit library and driver bundle](#).



# CHAPTER 2

---

## Installing from PyPI

---

On supported GNU/Linux systems like the Raspberry Pi, you can install the driver locally [from PyPI](#). To install for current user:

```
pip3 install adafruit-circuitpython-rgb-display
```

To install system-wide (this may be required in some cases):

```
sudo pip3 install adafruit-circuitpython-rgb-display
```

To install in a virtual environment in your current project:

```
mkdir project-name && cd project-name  
python3 -m venv .env  
source .env/bin/activate  
pip3 install adafruit-circuitpython-rgb-display
```



# CHAPTER 3

---

## Usage Example

---

```
import busio
import digitalio
from board import SCK, MOSI, MISO, D2, D3

from adafruit_rgb_display import color565
import adafruit_rgb_display.ilis341 as ilis341

# Configuration for CS and DC pins:
CS_PIN = D2
DC_PIN = D3

# Setup SPI bus using hardware SPI:
spi = busio.SPI(clock=SCK, MOSI=MOSI, MISO=MISO)

# Create the ILI9341 display:
display = ilis341.ILI9341(spi, cs=digitalio.DigitalInOut(CS_PIN),
                           dc=digitalio.DigitalInOut(DC_PIN))

# Main loop:
while True:
    # Clear the display
    display.fill(0)
    # Draw a red pixel in the center.
    display.pixel(120, 160, color565(255, 0, 0))
    # Pause 2 seconds.
    time.sleep(2)
    # Clear the screen blue.
    display.fill(color565(0, 0, 255))
    # Pause 2 seconds.
    time.sleep(2)
```



# CHAPTER 4

---

## Contributing

---

Contributions are welcome! Please read our [Code of Conduct](#) before contributing to help this project stay welcoming.



# CHAPTER 5

---

## Documentation

---

For information on building library documentation, please check out [this guide](#).



# CHAPTER 6

---

## Table of Contents

---

### 6.1 Simple test

Ensure your device works with this simple test.

Listing 1: examples/rgb\_display\_simpletest.py

```
1 # Quick test of TFT FeatherWing (ST7789) with Feather M0 or M4
2 # This will work even on a device running displayio
3 # Will fill the TFT black and put a red pixel in the center, wait 2 seconds,
4 # then fill the screen blue (with no pixel), wait 2 seconds, and repeat.
5 import time
6 import random
7 import digitalio
8 import board
9 import displayio
10
11 from adafruit_rgb_display.rgb import color565
12 import adafruit_rgb_display.st7789 as st7789
13
14 displayio.release_displays()
15
16 # Configuratoion for CS and DC pins (these are FeatherWing defaults on M0/M4):
17 cs_pin = digitalio.DigitalInOut(board.D5)
18 dc_pin = digitalio.DigitalInOut(board.D6)
19 reset_pin = digitalio.DigitalInOut(board.D9)
20
21 # Config for display baudrate (default max is 24mhz):
22 BAUDRATE = 24000000
23
24 # Setup SPI bus using hardware SPI:
25 spi = board.SPI()
26
27 # Create the ST7789 display:
```

(continues on next page)

(continued from previous page)

```

28 display = st7789.ST7789(spi, cs=cs_pin, dc=dc_pin, rst=reset_pin, baudrate=BAUDRATE)
29
30 # Main loop:
31 while True:
32     # Fill the screen red, green, blue, then black:
33     for color in ((255, 0, 0), (0, 255, 0), (0, 0, 255)):
34         display.fill(color565(color))
35     # Clear the display
36     display.fill(0)
37     # Draw a red pixel in the center.
38     display.pixel(display.width//2, display.height//2, color565(255, 0, 0))
39     # Pause 2 seconds.
40     time.sleep(2)
41     # Clear the screen a random color
42     display.fill(color565(random.randint(0, 255),
43                           random.randint(0, 255),
44                           random.randint(0, 255)))
45     # Pause 2 seconds.
46     time.sleep(2)

```

Listing 2: examples/rgb\_display\_ilis341test.py

```

1 # Quick test of TFT FeatherWing (ILI9341) with Feather M0 or M4
2 # Will fill the TFT black and put a red pixel in the center, wait 2 seconds,
3 # then fill the screen blue (with no pixel), wait 2 seconds, and repeat.
4 import time
5 import random
6 import busio
7 import digitalio
8 import board
9
10 from adafruit_rgb_display.rgb import color565
11 import adafruit_rgb_display.ilis341 as ilis341
12
13
14 # Configuration for CS and DC pins (these are FeatherWing defaults on M0/M4):
15 cs_pin = digitalio.DigitalInOut(board.D9)
16 dc_pin = digitalio.DigitalInOut(board.D10)
17
18 # Config for display baudrate (default max is 24mhz):
19 BAUDRATE = 24000000
20
21 # Setup SPI bus using hardware SPI:
22 spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)
23
24 # Create the ILI9341 display:
25 display = ilis341.ILI9341(spi, cs=cs_pin, dc=dc_pin, baudrate=BAUDRATE)
26
27 # Main loop:
28 while True:
29     # Fill the screen red, green, blue, then black:
30     for color in ((255, 0, 0), (0, 255, 0), (0, 0, 255)):
31         display.fill(color565(color))
32     # Clear the display
33     display.fill(0)
34     # Draw a red pixel in the center.

```

(continues on next page)

(continued from previous page)

```

35     display.pixel(display.width//2, display.height//2, color565(255, 0, 0))
36     # Pause 2 seconds.
37     time.sleep(2)
38     # Clear the screen a random color
39     display.fill(color565(random.randint(0, 255),
40                           random.randint(0, 255),
41                           random.randint(0, 255)))
42     # Pause 2 seconds.
43     time.sleep(2)

```

## 6.2 adafruit\_rgb\_display.rgb

Base class for all RGB Display devices

- Author(s): Radomir Dopieralski, Michael McWethy

**class** adafruit\_rgb\_display.rgb.**Display**(width, height, rotation)

Base class for all RGB display devices :param width: number of pixels wide :param height: number of pixels high

**fill**(color=0)

Fill the whole display with the specified color.

**fill\_rectangle**(x, y, width, height, color)

Draw a rectangle at specified position with specified width and height, and fill it with the specified color.

**hline**(x, y, width, color)

Draw a horizontal line.

**image**(img, rotation=None)

Set buffer to value of Python Imaging Library image. The image should be in 1 bit mode and a size equal to the display size.

**init**()

Run the initialization commands.

**pixel**(x, y, color=None)

Read or write a pixel at a given position.

**rotation**

Set the default rotation

**vline**(x, y, height, color)

Draw a vertical line.

**class** adafruit\_rgb\_display.rgb.**DisplaySPI**(spi, dc, cs, rst=None, width=1, height=1, baudrate=12000000, polarity=0, phase=0, \*, x\_offset=0, y\_offset=0, rotation=0)

Base class for SPI type devices

**read**(command=None, count=0)

SPI read from device with optional command

**reset**()

Reset the device

**write**(command=None, data=None)

SPI write to the device: commands and data

```
class adafruit_rgb_display.rgb.DummyPin
    Can be used in place of a DigitalInOut() when you don't want to skip it.

deinit()
    Dummy DigitalInOut_deinit

direction
    Dummy direction DigitalInOut property

pull
    Dummy pull DigitalInOut property

switch_to_input(*args, **kwargs)
    Dummy switch_to_input method

switch_to_output(*args, **kwargs)
    Dummy switch_to_output method

value
    Dummy value DigitalInOut property
```

adafruit\_rgb\_display.rgb.**color565**(r, g=0, b=0)  
Convert red, green and blue values (0-255) into a 16-bit 565 encoding. As a convenience this is also available in the parent adafruit\_rgb\_display package namespace.

## 6.3 adafruit\_rgb\_display.hx8353

A simple driver for the HX8353-based displays.

- Author(s): Radomir Dopieralski, Michael McWethy

```
class adafruit_rgb_display.hx8353.HX8353(spi, dc, cs, rst=None, width=128, height=128, rotation=0)
```

A simple driver for the HX8353-based displays.

```
>>> import busio
>>> import digitalio
>>> import board
>>> from adafruit_rgb_display import color565
>>> import adafruit_rgb_display.hx8353 as hx8353
>>> spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)
>>> display = hx8353.HX8383(spi, cs=digitalio.DigitalInOut(board.GPIO0),
...     dc=digitalio.DigitalInOut(board.GPIO15))
>>> display.fill(0x7521)
>>> display.pixel(64, 64, 0)
```

## 6.4 adafruit\_rgb\_display.ilim9341

A simple driver for the ILI9341/ILI9340-based displays.

- Author(s): Radomir Dopieralski, Michael McWethy

```
class adafruit_rgb_display.ilim9341.ILIM9341(spi, dc, cs, rst=None, width=240, height=320,
                                             baudrate=16000000, polarity=0, phase=0, rotation=0)
```

A simple driver for the ILI9341/ILI9340-based displays.

```
>>> import busio
>>> import digitalio
>>> import board
>>> from adafruit_rgb_display import color565
>>> import adafruit_rgb_display.ili9341 as ili9341
>>> spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)
>>> display = ili9341.ILI9341(spi, cs=digitalio.DigitalInOut(board.GPIO0),
...     dc=digitalio.DigitalInOut(board.GPIO15))
>>> display.fill(color565(0xff, 0x11, 0x22))
>>> display.pixel(120, 160, 0)
```

**scroll (dy=None)**  
Scroll the display by delta y

## 6.5 adafruit\_rgb\_display.s6d02a1

A simple driver for the S6D02A1-based displays.

- Author(s): Radomir Dopieralski, Michael McWethy

```
class adafruit_rgb_display.s6d02a1.S6D02A1(spi, dc, cs, rst=None, width=128, height=160,
                                             rotation=0)
```

A simple driver for the S6D02A1-based displays.

```
>>> import busio
>>> import digitalio
>>> import board
>>> from adafruit_rgb_display import color565
>>> import adafruit_rgb_display.s6d02a1 as s6d02a1
>>> spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)
>>> display = s6d02a1.S6D02A1(spi, cs=digitalio.DigitalInOut(board.GPIO0),
...     dc=digitalio.DigitalInOut(board.GPIO15), rst=digitalio.DigitalInOut(board.
...     GPIO16))
>>> display.fill(0x7521)
>>> display.pixel(64, 64, 0)
```

## 6.6 adafruit\_rgb\_display.ssd1331

A simple driver for the SSD1331-based displays.

- Author(s): Radomir Dopieralski, Michael McWethy

```
class adafruit_rgb_display(ssd1331.SSD1331(spi, dc, cs, rst=None, width=96, height=64,
                                              baudrate=16000000, polarity=0, phase=0, *,
                                              rotation=0))
```

A simple driver for the SSD1331-based displays.

```
import busio
import digitalio
import board
from adafruit_rgb_display import color565
import adafruit_rgb_display.ssd1331 as ssd1331
spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)
display = ssd1331.SSD1331(spi, cs=digitalio.DigitalInOut(board.GPIO0),
```

(continues on next page)

(continued from previous page)

```
dc=digitalio.DigitalInOut(board.GPIO15),  
rst=digitalio.DigitalInOut(board.GPIO16))  
  
display.fill(0x7521)  
display.pixel(32, 32, 0)
```

```
write (command=None, data=None)  
write procedure specific to SSD1331
```

## 6.7 adafruit\_rgb\_display.ssd1351

A simple driver for the SSD1351-based displays.

- Author(s): Radomir Dopieralski, Michael McWethy

```
class adafruit_rgb_display.ssd1351.SSD1351 (spi, dc, cs, rst=None, width=128, height=128,  
baudrate=16000000, polarity=0, phase=0, *,  
x_offset=0, y_offset=0, rotation=0)
```

A simple driver for the SSD1351-based displays.

```
>>> import busio  
>>> import digitalio  
>>> import board  
>>> from adafruit_rgb_display import color565  
>>> import adafruit_rgb_display.ssd1351 as ssd1351  
>>> spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)  
>>> display = ssd1351.SSD1351(spi, cs=digitalio.DigitalInOut(board.GPIO00),  
...     dc=digitalio.DigitalInOut(board.GPIO15), rst=digitalio.DigitalInOut(board.  
-GPIO16))  
>>> display.fill(0x7521)  
>>> display.pixel(32, 32, 0)
```

## 6.8 adafruit\_rgb\_display.st7735

A simple driver for the ST7735-based displays.

- Author(s): Radomir Dopieralski, Michael McWethy

```
class adafruit_rgb_display.st7735.ST7735 (spi, dc, cs, rst=None, width=128, height=128,  
baudrate=16000000, polarity=0, phase=0, *,  
x_offset=0, y_offset=0, rotation=0)
```

A simple driver for the ST7735-based displays.

```
>>> import busio  
>>> import digitalio  
>>> import board  
>>> from adafruit_rgb_display import color565  
>>> import adafruit_rgb_display.st7735 as st7735  
>>> spi = busio.SPI(clock=board.SCK, MOSI=board.MOSI, MISO=board.MISO)  
>>> display = st7735.ST7735(spi, cs=digitalio.DigitalInOut(board.GPIO00),  
...     dc=digitalio.DigitalInOut(board.GPIO15), rst=digitalio.DigitalInOut(board.  
-GPIO16))
```

(continues on next page)

(continued from previous page)

```
>>> display.fill(0x7521)
>>> display.pixel(64, 64, 0)
```

```
class adafruit_rgb_display.st7735.ST7735R(spi, dc, cs, rst=None, width=128, height=160,
                                             baudrate=16000000, polarity=0, phase=0, *,
                                             x_offset=0, y_offset=0, rotation=0, bgr=False)
```

A simple driver for the ST7735R-based displays.

**init()**

Run the initialization commands.



# CHAPTER 7

---

## Indices and tables

---

- genindex
- modindex
- search



---

## Python Module Index

---

### a

adafruit\_rgb\_display.hx8353, 16  
adafruit\_rgb\_display.ilis341, 16  
adafruit\_rgb\_display.rgb, 15  
adafruit\_rgb\_display.s6d02a1, 17  
adafruit\_rgb\_display.ssd1331, 17  
adafruit\_rgb\_display.ssd1351, 18  
adafruit\_rgb\_display.st7735, 18



---

## Index

---

### A

adafruit\_rgb\_display.hx8353 (*module*), 16  
adafruit\_rgb\_display.il19341 (*module*), 16  
adafruit\_rgb\_display.rgb (*module*), 15  
adafruit\_rgb\_display.s6d02a1 (*module*), 17  
adafruit\_rgb\_display.ssd1331 (*module*), 17  
adafruit\_rgb\_display.ssd1351 (*module*), 18  
adafruit\_rgb\_display.st7735 (*module*), 18

### C

color565 () (*in module adafruit\_rgb\_display.rgb*), 16

### D

deinit () (*adafruit\_rgb\_display.rgb.DummyPin method*), 16  
direction (*adafruit\_rgb\_display.rgb.DummyPin attribute*), 16  
Display (*class in adafruit\_rgb\_display.rgb*), 15  
DisplaySPI (*class in adafruit\_rgb\_display.rgb*), 15  
DummyPin (*class in adafruit\_rgb\_display.rgb*), 15

### F

fill () (*adafruit\_rgb\_display.rgb.Display method*), 15  
fill\_rectangle () (*adafruit\_rgb\_display.rgb.Display method*), 15

### H

hline () (*adafruit\_rgb\_display.rgb.Display method*), 15

HX8353 (*class in adafruit\_rgb\_display.hx8353*), 16

### I

IL19341 (*class in adafruit\_rgb\_display.il19341*), 16  
image () (*adafruit\_rgb\_display.rgb.Display method*), 15  
init () (*adafruit\_rgb\_display.rgb.Display method*), 15  
init () (*adafruit\_rgb\_display.st7735.ST7735R method*), 19

### P

pixel () (*adafruit\_rgb\_display.rgb.Display method*), 15  
pull (*adafruit\_rgb\_display.rgb.DummyPin attribute*), 16

### R

read () (*adafruit\_rgb\_display.rgb.DisplaySPI method*), 15  
reset () (*adafruit\_rgb\_display.rgb.DisplaySPI method*), 15  
rotation (*adafruit\_rgb\_display.rgb.Display attribute*), 15

### S

S6D02A1 (*class in adafruit\_rgb\_display.s6d02a1*), 17  
scroll () (*adafruit\_rgb\_display.il19341.IL19341 method*), 17  
SSD1331 (*class in adafruit\_rgb\_display.ssd1331*), 17  
SSD1351 (*class in adafruit\_rgb\_display.ssd1351*), 18  
ST7735 (*class in adafruit\_rgb\_display.st7735*), 18  
ST7735R (*class in adafruit\_rgb\_display.st7735*), 19  
switch\_to\_input () (*adafruit\_rgb\_display.rgb.DummyPin method*), 16  
switch\_to\_output () (*adafruit\_rgb\_display.rgb.DummyPin method*), 16

### V

value (*adafruit\_rgb\_display.rgb.DummyPin attribute*), 16  
vline () (*adafruit\_rgb\_display.rgb.Display method*), 15

### W

write () (*adafruit\_rgb\_display.rgb.DisplaySPI method*), 15  
write () (*adafruit\_rgb\_display.ssd1331.SSD1331 method*), 18