
AdafruitVCNL4010 Library Documentation

Release 1.0

Tony DiCola

Apr 10, 2020

Contents

| | | |
|----------|--------------------------------|-----------|
| 1 | Dependencies | 3 |
| 2 | Installing from PyPI | 5 |
| 3 | Usage Example | 7 |
| 4 | Contributing | 9 |
| 5 | Documentation | 11 |
| 6 | Table of Contents | 13 |
| 6.1 | Simple test | 13 |
| 6.2 | adafruit_vcnl4010 | 14 |
| 6.2.1 | Implementation Notes | 14 |
| 7 | Indices and tables | 17 |
| | Python Module Index | 19 |
| | Index | 21 |

CircuitPython module for the VCNL4010 proximity and light sensor.

CHAPTER 1

Dependencies

This driver depends on:

- Adafruit CircuitPython
- Bus Device

Please ensure all dependencies are available on the CircuitPython filesystem. This is easily achieved by downloading the [Adafruit library and driver bundle](#).

CHAPTER 2

Installing from PyPI

On supported GNU/Linux systems like the Raspberry Pi, you can install the driver locally [from PyPI](#). To install for current user:

```
pip3 install adafruit-circuitpython-vcnl4010
```

To install system-wide (this may be required in some cases):

```
sudo pip3 install adafruit-circuitpython-vcnl4010
```

To install in a virtual environment in your current project:

```
mkdir project-name && cd project-name  
python3 -m venv .env  
source .env/bin/activate  
pip3 install adafruit-circuitpython-vcnl4010
```


CHAPTER 3

Usage Example

See examples/vcnl4010_simpletest.py for an example of the usage.

CHAPTER 4

Contributing

Contributions are welcome! Please read our [Code of Conduct](#) before contributing to help this project stay welcoming.

CHAPTER 5

Documentation

For information on building library documentation, please check out [this guide](#).

CHAPTER 6

Table of Contents

6.1 Simple test

Ensure your device works with this simple test.

Listing 1: examples/vcnl4010_simpletest.py

```
1 # Simple demo of the VCNL4010 proximity and light sensor.
2 # Will print the proximity and ambient light every second.
3 # Author: Tony DiCola
4 import time
5
6 import board
7 import busio
8
9 import adafruit_vcnl4010
10
11
12 # Initialize I2C bus and VCNL4010 module.
13 i2c = busio.I2C(board.SCL, board.SDA)
14 sensor = adafruit_vcnl4010.VCNL4010(i2c)
15
16 # You can optionally adjust the sensor LED current.  The default is 200mA
17 # which is the maximum value.  Note this is only set in 10mA increments.
18 # sensor.led_current_mA = 120  # Set 120 mA LED current
19
20 # You can also adjust the measurement frequency for the sensor.  The default
21 # is 390.625 khz, but these values are possible to set too:
22 # - FREQUENCY_3M125: 3.125 Mhz
23 # - FREQUENCY_1M5625: 1.5625 Mhz
24 # - FREQUENCY_781K25: 781.25 Khz
25 # - FREQUENCY_390K625: 390.625 Khz (default)
26 # sensor.frequency = adafruit_vcnl4010.FREQUENCY_3M125  # 3.125 Mhz
27
```

(continues on next page)

(continued from previous page)

```
28 # Main loop runs forever printing the proximity and light level.
29 while True:
30     proximity = sensor.proximity # Proximity has no units and is a 16-bit
31     # value. The LOWER the value the further
32     # an object from the sensor (up to ~200mm).
33     print("Proximity: {0}".format(proximity))
34     ambient_lux = sensor.ambient_lux
35     print("Ambient light: {0} lux".format(ambient_lux))
36     time.sleep(1.0)
```

6.2 adafruit_vcnl4010

CircuitPython module for the VCNL4010 proximity and light sensor. See examples/vcnl4010_simpletest.py for an example of the usage.

- Author(s): Tony DiCola

6.2.1 Implementation Notes

Hardware:

- Adafruit [VCNL4010 Proximity/Light sensor breakout](#) (Product ID: 466)

Software and Dependencies:

- Adafruit CircuitPython firmware for the ESP8622 and M0-based boards: <https://github.com/adafruit/circuitpython/releases>
- Adafruit's Bus Device library: https://github.com/adafruit/Adafruit_CircuitPython_BusDevice

class adafruit_vcnl4010.VCNL4010 (i2c, address=19)

Vishay VCNL4010 proximity and ambient light sensor.

ambient

The detected ambient light in front of the sensor. This is a unit-less unsigned 16-bit value (0-65535) with higher values for more detected light. See the ambient_lux property for a value in lux.

ambient_lux

The detected ambient light in front of the sensor as a value in lux.

frequency

The frequency of proximity measurements. Must be a value of:

- FREQUENCY_3M125: 3.125 Mhz
- FREQUENCY_1M5625: 1.5625 Mhz
- FREQUENCY_781K25: 781.25 Khz
- FREQUENCY_390K625: 390.625 Khz (default)

See the datasheet for how frequency changes the proximity detection accuracy.

led_current

The current of the LED. The value is in units of 10mA and can only be set to 0 (0mA/off) to 20 (200mA). See the datasheet for how LED current impacts proximity measurements. The default is 200mA.

led_current_mA

The current of the LED in milli-amps. The value here is specified in a millamps from 0-200. Note that this value will be quantized down to a smaller less-accurate value as the chip only supports current changes in 10mA increments, i.e. a value of 123 mA will actually use 120 mA. See the datasheet for how the LED current impacts proximity measurements, and the led_current property to explicitly set values without quantization or unit conversion.

proximity

The detected proximity of an object in front of the sensor. This is a unit-less unsigned 16-bit value (0-65535) INVERSELY proportional to the distance of an object in front of the sensor (up to a max of ~200mm). For example a value of 10 is an object farther away than a value of 1000. Note there is no conversion from this value to absolute distance possible, you can only make relative comparisons.

CHAPTER 7

Indices and tables

- genindex
- modindex
- search

Python Module Index

a

[adafruit_vcnl4010](#), 14

Index

A

`adafruit_vcnl4010` (*module*), 14
`ambient` (*adafruit_vcnl4010.VCNL4010 attribute*), 14
`ambient_lux` (*adafruit_vcnl4010.VCNL4010 attribute*), 14

F

`frequency` (*adafruit_vcnl4010.VCNL4010 attribute*),
14

L

`led_current` (*adafruit_vcnl4010.VCNL4010 attribute*), 14
`led_current_mA` (*adafruit_vcnl4010.VCNL4010 attribute*), 14

P

`proximity` (*adafruit_vcnl4010.VCNL4010 attribute*),
15

V

`VCNL4010` (*class in adafruit_vcnl4010*), 14