

---

# **Adafruit VL53L0X Library Documentation**

*Release 1.0*

**Tony DiCola**

**Nov 25, 2019**



---

## Contents

---

<b>1</b>	<b>Dependencies</b>	<b>3</b>
<b>2</b>	<b>Installing from PyPI</b>	<b>5</b>
<b>3</b>	<b>Usage Example</b>	<b>7</b>
<b>4</b>	<b>Contributing</b>	<b>9</b>
<b>5</b>	<b>Documentation</b>	<b>11</b>
<b>6</b>	<b>Table of Contents</b>	<b>13</b>
6.1	Simple test .....	13
6.2	adafruit_v15310x .....	14
6.2.1	Implementation Notes .....	14
<b>7</b>	<b>Indices and tables</b>	<b>15</b>
	<b>Python Module Index</b>	<b>17</b>
	<b>Index</b>	<b>19</b>



CircuitPython driver for the VL53L0X distance sensor.



# CHAPTER 1

---

## Dependencies

---

This driver depends on:

- [Adafruit CircuitPython](#)
- [Bus Device](#)

Please ensure all dependencies are available on the CircuitPython filesystem. This is easily achieved by downloading the [Adafruit library and driver bundle](#).





## CHAPTER 2

---

### Installing from PyPI

---

On supported GNU/Linux systems like the Raspberry Pi, you can install the driver locally [from PyPI](#). To install for current user:

```
pip3 install adafruit-circuitpython-v15310x
```

To install system-wide (this may be required in some cases):

```
sudo pip3 install adafruit-circuitpython-v15310x
```

To install in a virtual environment in your current project:

```
mkdir project-name && cd project-name
python3 -m venv .env
source .env/bin/activate
pip3 install adafruit-circuitpython-v15310x
```



## CHAPTER 3

---

### Usage Example

---

See usage in the `examples/v15310x_simpletest.py` file.



## CHAPTER 4

---

### Contributing

---

Contributions are welcome! Please read our [Code of Conduct](#) before contributing to help this project stay welcoming.



## CHAPTER 5

---

### Documentation

---

For information on building library documentation, please check out [this guide](#).





## 6.1 Simple test

Ensure your device works with this simple test.

Listing 1: examples/vl53l0x\_simpletest.py

```
1 # Simple demo of the VL53L0X distance sensor.
2 # Will print the sensed range/distance every second.
3 import time
4
5 import board
6 import busio
7
8 import adafruit_vl53l0x
9
10 # Initialize I2C bus and sensor.
11 i2c = busio.I2C(board.SCL, board.SDA)
12 vl53 = adafruit_vl53l0x.VL53L0X(i2c)
13
14 # Optionally adjust the measurement timing budget to change speed and accuracy.
15 # See the example here for more details:
16 # https://github.com/pololu/vl53l0x-arduino/blob/master/examples/Single/Single.ino
17 # For example a higher speed but less accurate timing budget of 20ms:
18 #vl53.measurement_timing_budget = 20000
19 # Or a slower but more accurate timing budget of 200ms:
20 #vl53.measurement_timing_budget = 200000
21 # The default timing budget is 33ms, a good compromise of speed and accuracy.
22
23 # Main loop will read the range and print it every second.
24 while True:
25     print('Range: {0}mm'.format(vl53.range))
26     time.sleep(1.0)
```

## 6.2 adafruit\_vl53l0x

CircuitPython driver for the VL53L0X distance sensor. This code is adapted from the pololu driver here: <https://github.com/pololu/vl53l0x-arduino>

See usage in the examples/vl53l0x\_simpletest.py file.

- Author(s): Tony DiCola

### 6.2.1 Implementation Notes

#### Hardware:

- Adafruit VL53L0X Time of Flight Distance Sensor - ~30 to 1000mm (Product ID: 3317)

#### Software and Dependencies:

- Adafruit CircuitPython firmware for the ESP8622 and M0-based boards: <https://github.com/adafruit/circuitpython/releases>
- Adafruit's Bus Device library: [https://github.com/adafruit/Adafruit\\_CircuitPython\\_BusDevice](https://github.com/adafruit/Adafruit_CircuitPython_BusDevice)

**class** `adafruit_vl53l0x.VL53L0X` (*i2c*, *address=41*, *io\_timeout\_s=0*)  
Driver for the VL53L0X distance sensor.

**measurement\_timing\_budget**

The measurement timing budget in microseconds.

**range**

Perform a single reading of the range for an object in front of the sensor and return the distance in millimeters.

**signal\_rate\_limit**

The signal rate limit in mega counts per second.

## CHAPTER 7

---

### Indices and tables

---

- `genindex`
- `modindex`
- `search`



**a**

`adafruit_vl53l0x`, 13



## A

adafruit\_vl53l0x (*module*), 13

## M

measurement\_timing\_budget  
(*adafruit\_vl53l0x.VL53L0X attribute*), 14

## R

range (*adafruit\_vl53l0x.VL53L0X attribute*), 14

## S

signal\_rate\_limit (*adafruit\_vl53l0x.VL53L0X attribute*), 14

## V

VL53L0X (*class in adafruit\_vl53l0x*), 14